

# LSI-11

TRAPS TEST  
MD-11-DVKAD-B

EP DVKAD B DL B  
COPYRIGHT 1977  
FICHE 1 OF 1

MAR 1977  
**digital**  
MADE IN USA

The image displays a grid of 60 small tables, arranged in 10 rows and 6 columns. Each table contains technical data, likely test results or configuration parameters for the LSI-11. The text within the tables is small and difficult to read, but the layout is consistent across all cells. The tables are organized into a structured grid, with each cell containing a separate set of data.

LSI-11



.REM !

1  
2  
3  
4  
5  
6  
7  
8  
9  
10  
11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43

IDENTIFICATION

PRODUCT NAME:	DVKAD-B (LSI-11 ONLY)
DATE CREATED:	FEBRUARY, 1977
MAINTAINER:	DIAGNOSTIC GROUP
AUTHOR:	AL LOSCHAK
REVISED BY:	M. MCNALLY            JUNE 1976

COPYRIGHT (C) 1975,1977 DIGITAL EQUIPMENT CORP., MAYNARD, MASS.

THIS SOFTWARE IS FURNISHED TO PURCHASER UNDER A LICENSE FOR USE ON A SINGLE COMPUTER SYSTEM AND CAN BE COPIED (WITH INCLUSION OF DEC'S COPYRIGHT NOTICE) ONLY FOR USE IN SUCH SYSTEM, EXCEPT AS MAY OTHERWISE BE PROVIDED IN WRITING BY DEC.

THE INFORMATION IN THIS DOCUMENT IS SUBJECT TO CHANGE WITHOUT NOTICE AND SHOULD NOT BE CONSTRUED AS A COMMITMENT BY DIGITAL EQUIPMENT CORPORATION.

DEC ASSUMES NO RESPONSIBILITY FOR THE USE OR RELIABILITY OF ITS SOFTWARE ON EQUIPMENT WHICH IS NOT SUPPLIED BY DEC.



44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56

- 1. ABSTRACT  
THIS IS A TEST OF ALL OPERATIONS AND INSTRUCTIONS THAT CAUSE TRAPS, ODDITIES OF REGISTER 6, INTERRUPTS, THE RESET AND WAIT INSTRUCTIONS.
- 2. REQUIREMENTS
  - 2.1 EQUIPMENT  
LSI-11 STANDARD COMPUTER WITH AN SLU UNIT AND 4K OF MEMORY
  - 2.2 STORAGE  
2.2.1 PROGRAM STORAGE - THE ROUTINE USES 4K MEMORY
- 3. LOADING PROCEDURE
  - 3.1 METHOD  
PROCEDURE FOR NORMAL ABSOLUTE TAPES SHOULD BE FOLLOWED.



67  
68  
69  
70  
71  
72  
73  
74  
75  
76  
77  
78  
79  
80  
81  
82  
83  
84  
85  
86  
87  
88  
89  
90  
91  
92  
93  
94  
95  
96  
97  
98  
99  
100  
101  
102  
103

## 4. STARTING PROCEDURE

THE PROGRAM STARTS AT 200. IF THIS PROGRAM RUNS UNDER APT NO CHANGE IS NECESSARY. IF THIS PROGRAM RUNS ALONE THE OPERATOR HAS THE FOLLOWING OPTIONS BY SETTING THE SOFTWARE SWITCH REGISTER (LOCATION 422)

BIT 6=1 (100 OCTAL) IF WE HAVE EIS AND FIS OPTION

BIT 5=1 (40 OCTAL) IF WE WANT TO SUPRESS "END OF PASS" TYPEOUT

BIT 4=1 (20 OCTAL) WILL NOT ALLOW OPCODES 75400-76777 TO DO RESERVED INSTRUCTIONS TRAPS IN THE LAST TEST OF THIS DIAGNOSTIC.

BIT 3=1 (10 OCTAL) WILL NOT ALLOW OPCODES 170000-177777 TO DO RESERVED INSTRUCTIONS TRAPS IN THE LAST TEST OF THIS DIAGNOSTIC.

BIT 2=1 (4 OCTAL) WILL NOT ALLOW OPCODES 76030-76057 (DIS RESERVED OPCODE SPACE) NOR EIS OPCODES TO DO RESERVED INSTRUCTION TRAPS IN THE LAST TEST OF THIS DIAGNOSTIC

THE PROGRAM STARTS AT 200.  
IF IT IS DESIRED TO RESET THE PASS COUNT BACK TO ZERO START AT LOCATION 210.

## 4.3 PROGRAM AND/OR OPERATOR ACTION

LOAD PROGRAM INTO MEMORY. (BOTTOM 4K)  
SET THE DESIRED SWITCH REGISTER BITS, IF ANY.  
LOAD ADDRESS.  
START.

THE PROGRAM WILL PRINT END OF PASS AFTER THE 1ST ITERATION AND THEN PRINT IT EVERY 15 TIMES; APROXIMATELY 2 MINUTES.



104  
105  
106  
107  
108  
109  
110  
111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136

## 5. OPERATION PROCEDURE

## 5.2 SUBROUTINE ABSTRACTS

5.2.1 TRAPCATCHER

THIS IS A SERIES OF INSTRUCTIONS DESIGNED TO DETECT AND ISOLATE UNEXPECTED TRAPS AND INTERRUPTS, THAT OCCUR IN THE TRAP AND INTERRUPT VECTOR AREA OF MEMORY.

THE PRINCIPLE OF THIS ROUTINE IS: THE VECTOR ENTRANCE ADDRESS POINTS TO THE NEXT SEQUENTIAL WORD WHICH WILL CONTAIN A HALT (000000) (THIS LOCATION IS ALSO THE STATUS WORD FOR THAT VECTOR ENTRANCE. BUT THIS WILL HAVE NO EFFECT ON IT.

IF A HALT OCCURS IN THE TRAP OR INTERRUPT VECTOR AREA, REGISTER SIX SHOULD BE EXAMINED TO DETERMINE ITS CONTENTS, THEN USE REGISTER SIX CONTENTS AS AN ADDRESS TO DETERMINE THE LOCATION THE PROGRAM WAS AT, WHEN THE INTERRUPT OR TRAP OCCURRED. (MEMORY AS SPECIFIED BY R6 CONTAINS THE PC OF THE INSTRUCTION FOLLOWING THE INSTRUCTION WHERE THE TRAP OCCURRED. ALSO THE CONTENTS OF 'STESTN' CONTAIN THE TEST NUMBER THAT IT WAS DOING BEFORE IT TRAPPED.

## 5.3 PROGRAM AND/OR OPERATOR ACTION

5.3.1 LOADING AND STARTING AT 200 STARTS THE TEST. IF AN ERROR IS DETECTED, THERE WILL BE A HALT.



137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170

6. ERRORS

6.1 ALL ERRORS WILL CAUSE A HALT.  
THE PC+2 OF THE HALT INSTRUCTION IS PRINTED  
ON THE CONSOLE DEVICE BY THE LSI-11.

6.1.1 THE PROGRAM CHECKS TO SEE THAT THE P.C. DOESN'T JUMP  
WITHIN THE TESTS, BY A SEQUENCE COUNT CALLED 'STSTN'  
THIS TEST IS A SEQUENTIAL INCREMENT AND COMPARE COUNT.

EX: CODE

INC @#STESTN ;UPDATE TEST NUMBER  
CMP #N,@#STESTN ;SEQUENCE ERROR?  
BNE SOME LOCATION ;BRANCH TO ERROR HALT ON SEQ ERROR  
IMPORTANT

\*\*\*\*\*

IF AN ERROR IS DETECTED ;IT COULD BE BECAUSE OF TWO REASONS.  
A) WRONG TEST NUMBER  
B) ERROR IN THE PRESENT TEST.

////////////////////////////////////  
THE TEST SEQUENCE LOCATION "TESTN" SHOULD BE CHECKED FIRST  
TO SEE IF IT MATCHES THE PRESENT TEST.  
IF IT DOESN'T MATCH ; THEN THE CONTENTS OF THIS LOCATION  
TELL YOU WHICH TEST IT WAS DOING BEFORE IT HALTED.  
////////////////////////////////////

6.2 ERROR RECOVERY  
ON TRAP ERRORS - RESTART AT STARTING ADDRESS



171  
 172  
 173  
 174  
 175  
 176  
 177  
 178  
 179  
 180  
 181  
 182  
 183  
 184  
 185  
 186  
 187  
 188  
 189  
 190  
 191  
 192  
 193  
 194  
 195  
 196  
 197  
 198  
 199  
 200  
 201  
 202  
 203  
 204  
 205

7. RESTRICTIONS  
 7.1 STARTING RESTRICTION

NONE

7.2 OPERATIONAL RESTRICTION

NONE

8. MISCELLANEOUS  
 THERE IS A TEST THAT WILL CHECK THAT ODD ADDRESSING  
 WILL IGNORE BIT "0"

8.1 EXECUTION TIME

FOR ONE PASS APROXIMATELY 8 SECONDS; THEN IT TYPES  
 "END OF PASS" APROXIMATELY EVERY 2 MINUTES.

9. PROGRAM DESCRIPTION

THIS PROGRAM CHECKS THAT ON ALL TRAP OPERATIONS REGISTER  
 6 IS DECREMENTED THE CORRECT AMOUNT, THAT THE CORRECT  
 PC IS SAVED ON THE STACK, THAT THE OLD CONDITION CODES AND  
 PRIORITY ARE PLACED ON THE STACK AND THAT THE NEW STATUS AND  
 CONDITION CODES ARE CORRECT. BOTH THE "TRAP" AND "EMT"  
 TRAP INSTRUCTIONS ARE TESTED TO SEE THAT ALL COMBINATIONS WILL  
 TRAP. CHECKED ALSO ARE THE RTT AND THE RTI INSTRUCTIONS AND THAT ALL  
 RESTRICTED INSTRUCTIONS WILL TRAP. VERIFICATION OF THE "BPT" INSTRUCTION (00003  
 WHICH IS USED FOR SOFTWARE DEBUG ROUTINES: ODT, DDT, IS DONE.  
 ALSO, THE TRACE BIT IS CHECKED TO SEE IF IT CAUSES A TRAP.  
 SPECIAL CHECKS ARE MADE TO SEE IF BUS  
 ERROR TRAPS OCCUR ON NON-EXISTENT MEMORY.

!



H01

MAIN. MACY11 27(1006) 17-FEB-77 15:39 PAGE 7  
DVKADB.P11 17-FEB-77 15:34

SEQ 0009

206  
207



208  
 209 000000\* 000000G  
 210  
 211  
 212  
 213  
 214  
 215 000007  
 216 000006  
 217 000003  
 218 000000  
 219 000001  
 220 000002  
 221 000000  
 222 104400  
 223 104000  
 224 000003  
 225 000004  
 226 000004  
 227 000014  
 228 000030  
 229 000020  
 230 000034  
 231 177564  
 232 177560  
 233 177564  
 234 177566  
 235 000240  
 236 000240  
 237 000007  
 238 000010  
 239 004700  
 240 000100  
 241 000404  
 242 000402  
 243

LISTING

.NLIST MD,CND,MC  
 .LIST ME

PC=%7  
 SP=%6  
 TAB=%3  
 RO=%0  
 LAST=%1  
 FIRST=%2  
 HLT=HALT  
 TRAP=104400  
 EMT=104000  
 TRT=3  
 ITRAP5=4  
 RTRAP5=4  
 RTRAP4=14  
 RTRAP3=30  
 RTRAP2=20  
 RTRAP1=34  
 TTCSR=177564  
 TRCSR=177560  
 TPS=177564  
 TPB=177566  
 BELL=240  
 NOP=240  
 TRAPA=000007  
 RTRAP=10  
 ILLA=004700  
 ILLB=100  
 \$STNM=\$TESTN  
 \$ERROR=\$FATAL  
 .ABS

;RESERVED INST AND ILLEGAL ADDRESSES  
 ;FOR TRACE TRAP  
 ;FOR EMULATOR TRAP  
 ;FOR IOT TRAP  
 ;FOR TRAP INST

244  
245  
246 000400  
247  
248  
249  
250  
251 000400  
252 000046  
253 000046 013226  
254 000052  
255 000052 000000  
256 000400  
257  
258  
259  
260  
261 000400  
262 000400 000000  
263 000402 000000  
264 000404 000000  
265 000406 000000  
266 000410 000000  
267 000412 000000  
268 000414 000000  
269 000416 000000  
270 000420  
271 000420 000  
272 000421 000  
273 000422 000000  
274 000424 000000  
275 000426 000000  
276  
277  
278  
279  
280  
281  
282 000430 000  
283 000431 000  
284  
285  
286  
287  
288 000432 000000  
289  
290 000434 000  
291 000435 000  
292 000436 000000  
293 000440 000  
294 000441 000  
295 000442 000000  
296 000444 000  
297 000445 000  
298 000446 000000  
299 000450

.=400  
.SBTTL ACT11 HOOKS

\*\*\*\*\*

:HOOKS REQUIRED BY ACT11

\$SVPC=. ;SAVE PC

.=46

\$ENDAD ;;1)SET LOC.46 TO ADDRESS OF \$ENDAD IN .SEOP

.=52

.WORD 0 ;;2)SET LOC.52 TO ZERO

.=\$SVPC

;; RESTORE PC

.SBTTL APT MAILBOX-ETABLE

\*\*\*\*\*

.EVEN

\$MAIL: ;APT MAILBOX

\$MSGTY: .WORD AMSGTY ;MESSAGE TYPE CODE

\$FATAL: .WORD AFATAL ;FATAL ERROR NUMBER

\$TESTN: .WORD ATESTN ;TEST NUMBER

\$PASS: .WORD APASS ;PASS COUNT

\$DEVCT: .WORD ADEVCT ;DEVICE COUNT

\$UNIT: .WORD AUNIT ;I/O UNIT NUMBER

\$MSGAD: .WORD AMSGAD ;MESSAGE ADDRESS

\$MSGLG: .WORD AMSGLG ;MESSAGE LENGTH

\$ETABLE: ;APT ENVIRONMENT TABLE

\$ENV: .BYTE AENV ;ENVIRONMENT BYTE

\$ENVM: .BYTE AENVM ;ENVIRONMENT MODE BITS

\$SWREG: .WORD ASWREG ;APT SWITCH REGISTER

\$USWR: .WORD AUSWR ;USER SWITCHES

\$CPUOP: .WORD ACPUOP ;CPU TYPE, OPTIONS

BITS 15-11=CPU TYPE

11/04=01,11/05=02,11/20=03,11/40=04,11/45=05

11/70=06,PDQ=07,Q=10

BIT 10=REAL TIME CLOCK

BIT 9=FLOATING POINT PROCESSOR

BIT 8=MEMORY MANAGEMENT

\$MAMS1: .BYTE AMAMS1 ;HIGH ADDRESS, M.S. BYTE

\$MTYP1: .BYTE AMTYP1 ;MEM. TYPE, BLK#1

MEM. TYPE BYTE -- (HIGH BYTE)

900 NSEC CORE=001

300 NSEC BIPOLAR=002

500 NSEC MOS=003

\$MADR1: .WORD AMADR1 ;HIGH ADDRESS, BLK#1

MEM. LAST ADDR.=3 BYTES, THIS WORD AND LOW OF "TYPE" ABOVE

\$MAMS2: .BYTE AMAMS2 ;HIGH ADDRESS, M.S. BYTE

\$MTYP2: .BYTE AMTYP2 ;MEM. TYPE, BLK#2

\$MADR2: .WORD AMADR2 ;MEM. LAST ADDRESS, BLK#2

\$MAMS3: .BYTE AMAMS3 ;HIGH ADDRESS, M.S. BYTE

\$MTYP3: .BYTE AMTYP3 ;MEM. TYPE, BLK#3

\$MADR3: .WORD AMADR3 ;MEM. LAST ADDRESS, BLK#3

\$MAMS4: .BYTE AMAMS4 ;HIGH ADDRESS, M.S. BYTE

\$MTYP4: .BYTE AMTYP4 ;MEM. TYPE, BLK#4

\$MADR4: .WORD AMADR4 ;MEM. LAST ADDRESS, BLK#4

\$ETEND:



```

300
301
302
303
304
305
306      000450
307      000024
308 000024 000200
309      000044
310 000044 000450
311      000450
312
313
314
315
316 000450
317 000450 000000
318 000452 000400
319 000454 000011
320 000456 000011
321 000460 000000
322 000462 000024

```

```

.MEXIT
.SBTTL  APT PARAMETER BLOCK

```

```

;*****
;SET LOCATIONS 24 AND 44 AS REQUIRED FOR APT
;*****
.SX=      ;;SAVE CURRENT LOCATION
.=24     ;;SET POWER FAIL TO POINT TO START OF PROGRAM
200      ;;FOR APT START UP
.=44     ;;POINT TO APT INDIRECT ADDRESS PNTR.
$APTHDR  ;;POINT TO APT HEADER BLOCK
.=.SX    ;;RESET LOCATION COUNTER
;*****
;SETUP APT PARAMETER BLOCK AS DEFINED IN THE APT-PDP11 DIAGNOSTIC
;INTERFACE SPEC.

```

```

$APTHD:
$HIBTS: .WORD 0      ;;TWO HIGH BITS OF 18 BIT MAILBOX ADDR.
$MBADR: .WORD $MAIL  ;;ADDRESS OF APT MAILBOX (BITS 0-15)
$STMT:  .WORD 11     ;;RUN TIM OF LONGEST TEST
$PASTM: .WORD 11     ;;RUN TIME IN SECS. OF 1ST PASS ON 1 UNIT (QUICK VERIFY)
$UNITM: .WORD 0      ;;ADDITIONAL RUN TIME (SECS) OF A PASS FOR EACH ADDITIONAL UNIT
        .WORD $ETEND-$MAIL/2 ;;LENGTH MAILBOX-ETABLE(WORDS)

```

```

323
324
325      000200      000200      . =200
326 000200 000167 000276      JMP      START
327      000210      000210      . =210
328 000210 005037 000406      CLR      @#SPASS      ;CLEAR THE PASS COUNT
329 000214 000167 000262      JMP      START
330      000500      000500      . =500
331 000500 000000      BUFF: 00000
332 000502 012767 013276 177314  START: MOV      #PWRDN,24      ;SET UP THE POWER DOWN VECTOR
333 000510 012767 000340 177310      MOV      #340,26      ;SET UP POWER DOWN PRIORITY
334 000516 105767 177676      TSTB     $ENV          ;ARE WE UNDER APT?
335 000522 001023      BNE     BEGIN          ;YES
336 000524 005067 177671      CLR     $ENVM
337 000530 005067 177672      CLR     $CPUOP
338 000534 132767 000040 177660      BITB    #40,$SWREG      ;DO WE PRINT END OF PASS
339 000542 001403      BEQ     1$             ;YES
340 000544 152767 000040 177647      BISB    #40,$ENVM
341
342 000552 016700 177644      1$:  MOV     $SWREG,R0      ;GET CONTENT OF $SWREG
343 000556 032700 000100      BIT     #100,R0        ;DO WE HAVE EIS,FIS OPTION?
344 000562 001403      BEQ     BEGIN          ;NO
345 000564 052767 000300 177634      BIS     #300,$CPUOP    ;YES SET UP LOCATION #CPUOP
346
347
348
349 000572 012737 177777 013256  BEGIN: MOV     #-1,@#PASSPT
350 000600 012702 000400      RESTR: MOV     #MSGTY,%2
351 000604 005067 177570      CLR     $MSGTY
352 000610 005067 177570      CLR     $STNM
353 000614 005067 177562      CLR     $ERROR
354 000620 000167 000026      JMP     TST1
355 000624 000000      K1:    0
356 000626 000000      K2:    0
357 000630 000000      K3:    0
358 000632 000000      K4:    0
359 000634 000000      K5:    0
360 000636 000000      K6:    0
361 000640 052525      K7:    052525
362 000642 052400      K10:   052400
363 000644 000000      K11:   0
364 000646 000000      K12:   0
365 000650 000000      HERE:  0
    
```



# MO1

```

366
367
368 ;*****
369 ;TEST 1 TEST AUTO INCREMENT AND DECREMENT OF R6 FOR WORD AND BYTES
370 ;*****
370 000652 005237 000404          TST1:  INC  @#STESTN      ;UPDATE TEST NUMBER
371 000656 022737 000001 000404  CMP    #1,@#STESTN    ;SEQUENCE ERROR?
372 000664 001124                BNE    TST2-12 ;BR TO ERROR HALT ON SEQ ERROR
373 000666 005006                R6TST: CLR    %6
374 000670 112667 177754          MOVB  (6)+,HERE      ;SIX SHOULD INCREMENT BY TWO
375 000674 020627 000002          CMP    %6,#2
376 000700 001405                BEQ    1$
377 000702 012737 000001 000402  MOV    #1,@#$FATAL   ;MOVE TO MAILBOX # ***** 1 *****
378 000710 005212                INC    (R2)          ;SET MSGTYP TO FATAL ERROR
379 000712 000000                HALT                ;R6 DID NOT AUTO INCREMENT BY TWO
380                                     ; TO SCOPE REPLACE HALT W/ 240
381                                     ; AND REPLACE NEXT INST W/ 764
382
383 000714 012706 001000          1$:   MOV    #1000,%6
384 000720 114667 177724          MOVB  -(6),HERE      ;SHOULD DECREMENT BY TWO
385 000724 020627 000776          CMP    %6,#776
386 000730 001405                BEQ    2$
387 000732 012737 000002 000402  MOV    #2,@#$FATAL   ;MOVE TO MAILBOX # ***** 2 *****
388 000740 005212                INC    (R2)          ;SET MSGTYP TO FATAL ERROR
389 000742 000000                HALT                ;R6 DID NOT AUTO DECREMENT BY 2
390                                     ; TO SCOPE REPLACE HALT W/ 240
391                                     ; AND REPLACE NEXT INST W/ 750
392
393 000744 005006                2$:   CLR    %6
394 000746 112626                MOVB  (6)+,(6)+      ;DOUBLES AUTO INCREMENT OF R6
395 000750 020627 000004          CMP    %6,#4
396 000754 001405                BEQ    3$
397 000756 012737 000003 000402  MOV    #3,@#$FATAL   ;MOVE TO MAILBOX # ***** 3 *****
398 000764 005212                INC    (R2)          ;SET MSGTYP TO FATAL ERROR
399 000766 000000                HALT                ;WRONG AUTO INCREMENT OF R6
400                                     ; TO SCOPE REPLACE HALT W/ 240
401                                     ; AND REPLACE NEXT INST W/ 736
402
403 000770 005006                3$:   CLR    %6
404 000772 005004                CLR    %4
405 000774 122624                CMPB  (6)+,(4)+      ;TEST INCREMENT OF R6
406 000776 020627 000002          CMP    %6,#2
407 001002 001405                BEQ    4$
408 001004 012737 000004 000402  MOV    #4,@#$FATAL   ;MOVE TO MAILBOX # ***** 4 *****
409 001012 005212                INC    (R2)          ;SET MSGTYP TO FATAL ERROR
410 001014 000000                HALT                ;WRONG INCREMENT OF R6
411                                     ; TO SCOPE REPLACE HALT W/ 240
412                                     ; AND REPLACE NEXT INST W/ 723
413
414 001016 005006                4$:   CLR    %6
415 001020 005004                CLR    %4
416 001022 122426                CMPB  (4)+,(6)+      ;TEST INCREMENT OF R6
417 001024 020627 000002          CMP    %6,#2
418 001030 001405                BEQ    5$
419 001032 012737 000005 000402  MOV    #5,@#$FATAL   ;MOVE TO MAILBOX # ***** 5 *****
420 001040 005212                INC    (R2)          ;SET MSGTYP TO FATAL ERROR
421 001042 000000                HALT                ;WRONG INCREMENT OF R6

```





```

456
457
458
459
460 001150 005237 000404
461 001154 022737 000002 000404
462 001162 001137
463 001164 012767 123456 177442
464 001172 012767 050505 177424
465 001200 012705 000624
466 001204 012706 000634
467 001210 112625
468 001212 022767 050456 177404
469 001220 001405
470 001222 012737 000011 000402
471 001230 005212
472 001232 000000
473
474
475
476 001234 012767 123456 177372 1S:
477 001242 012767 050505 177354
478 001250 012705 000624
479 001254 012706 000636
480 001260 114625
481 001262 026727 177336 050456
482 001270 001405
483 001272 012737 000012 000402
484 001300 005212
485 001302 000000
486
487
488
489 001304 012767 123456 177312 2S:
490 001312 012767 050505 177314
491 001320 012705 000624
492 001324 012706 000634
493 001330 112526
494 001332 022767 050456 177274
495 001340 001405
496 001342 012737 000013 000402
497 001350 005212
498 001352 000000
499
500
501
502 001354 012767 123456 177242 3S:
503 001362 012767 050505 177244
504 001370 012705 000625
505 001374 012706 000634
506 001400 112526
507 001402 026727 177226 050647
508 001410 001405
509 001412 012737 000014 000402
510 001420 005212
511 001422 000000

```

```

*****
:TEST 2 TEST TRANSFER OF BYTE USING R6
*****
†ST2:  INC  @#STESTN      ;UPDATE TEST NUMBER
        CMP  #2,@#STESTN ;SEQUENCE ERROR?
        BNE  TST3-12 ;BR TO ERROR HALT ON SEQ ERROR
        MOV  #123456,K5
        MOV  #050505,K1
        MOV  #K1,%5      ;%5=(050505)K1
        MOV  #K5,%6      ;%6=(123456)K5
        MOVB (6)+,(5)+   ;LOW .BYTE OF R6 TO R5
        CMP  #050456,K1
        BEQ  1S
        MOV  #11,@#SFATAL ;MOVE TO MAILBOX # ***** 11 *****
        INC  (R2)         ;SET MSGTYP TO FATAL ERROR
        HALT              ;FALSE TRANSFER OF .BYTE
                          ; TO SCOPE REPLACE HALT W/ 240
                          ; AND REPLACE NEXT INST W/ 753

1S:    MOV  #123456,K5
        MOV  #050505,K1
        MOV  #K1,%5      ;%5(050505)K1
        MOV  #K6,%6      ;%6(123456)K5
        MOVB -(6),(5)+   ;LOW .BYTE OF R6 TO R5 (DECREMENT)
        CMP  K1,#050456
        BEQ  2S
        MOV  #12,@#SFATAL ;MOVE TO MAILBOX # ***** 12 *****
        INC  (R2)         ;SET MSGTYP TO FATAL ERROR
        HALT              ;FALSE R6 .BYTE TRANSFER
                          ; TO SCOPE REPLACE HALT W/ 240
                          ; AND REPLACE NEXT INST W/ 727

2S:    MOV  #123456,K1
        MOV  #050505,K5
        MOV  #K1,%5      ;(123456)
        MOV  #K5,%6      ;(050505)
        MOVB (5)+,(6)+   ;LOW OF R5 TO LOW OF R6
        CMP  #050456,K5
        BEQ  3S
        MOV  #13,@#SFATAL ;MOVE TO MAILBOX # ***** 13 *****
        INC  (R2)         ;SET MSGTYP TO FATAL ERROR
        HALT              ;FALSE R6 .BYTE TRANSFER
                          ; TO SCOPE REPLACE HALT W/ 240
                          ; AND REPLACE NEXT INST W/ 703

3S:    MOV  #123456,K1
        MOV  #050505,K5
        MOV  #K1+1,%5    ;123456
        MOV  #K5,%6      ;050505
        MOVB (5)+,(6)+   ;HIGH OF R5 TO LOW OF R6
        CMP  K5,#050647
        BEQ  4S
        MOV  #14,@#SFATAL ;MOVE TO MAILBOX # ***** 14 *****
        INC  (R2)         ;SET MSGTYP TO FATAL ERROR
        HALT              ;FALSE R6 .BYTE TRANSFER

```





```

527
528
529
530
531 001474 005237 000404
532 001500 022737 000003 000404
533 001506 001103
534 001510 126767 177124 177123
535 001516 001405
536 001520 012737 000016 000402
537 001526 005212
538 001530 000000
539
540
541
542 001532 126767 177103 177100 1$: CMPB K7+1,K7 ;COMPARE ODD TO .EVEN SAME .WORD
543 001540 001405 BEQ 2$
544 001542 012737 000017 000402 MOV #17,@#$FATAL ;MOVE TO MAILBOX # ***** 17 *****
545 001550 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
546 001552 000000 HALT ;ODD TO .EVEN .BYTE FAILURE
547 ; TO SCOPE REPLACE HALT W/ 240
548 ; AND REPLACE NEXT INST W/ 755
549
550 001554 126767 177063 177056 2$: CMPB K10+1,K7 ;SEQUENTIAL .BYTES
551 ;DIFFERENT .WORDS
552 001562 001462 BEQ TST4
553 001564 012737 000020 000402 MOV #20,@#$FATAL ;MOVE TO MAILBOX # ***** 20 *****
554 001572 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
555 001574 000000 HALT ;ODD TO .EVEN FAILED
556 ; TO SCOPE REPLACE HALT W/ 240
557 ; AND REPLACE NEXT INST W/ 744
558
559 001576 126767 177040 177032 CMPB K10,K6
560 001604 001405 BEQ 3$
561 001606 012737 000021 000402 MOV #21,@#$FATAL ;MOVE TO MAILBOX # ***** 21 *****
562 001614 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
563 001616 000000 HALT ;.EVEN TO EVEN FAILED
564 ; TO SCOPE REPLACE HALT W/ 240
565 ; AND REPLACE NEXT INST W/ 733
566 001620 126767 177015 177015 3$: CMPB K7+1,K10+1
567 001626 001405 BEQ 4$
568 001630 012737 000022 000402 MOV #22,@#$FATAL ;MOVE TO MAILBOX # ***** 22 *****
569 001636 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
570 001640 000000 HALT ;ODD TO ODD FAILED
571 ; TO SCOPE REPLACE HALT W/ 240
572 ; AND REPLACE NEXT INST W/ 722
573
574 001642 126767 176774 176773 4$: CMPB K10,K10+1
575 001650 001005 BNE 5$
576 001652 012737 000023 000402 MOV #23,@#$FATAL ;MOVE TO MAILBOX # ***** 23 *****
577 001660 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
578 001662 000000 HALT ;LOW TO HIGH IN SAME .WORD FAILED
579 ; TO SCOPE REPLACE HALT W/ 240
580 ; AND REPLACE NEXT INST W/ 711
581
582 001664 126767 176753 176751 5$: CMPB K10+1,K10+1
    
```

## E02

.MAIN. MACY11 27(1006) 17-FEB-77 15:39 PAGE 17  
 DVKADB.P11 17-FEB-77 15:34 T3

TEST BYTE OPERATION WITH SEQUENTIAL ODD; .EVEN ADDRESS

SEQ 0019

583	001672	001405				BEG	65		
584	001674	012737	000024	000402		MOV	#24, 3#SFATAL	; MOVE TO MAILBOX # ***** 24 *****	
585	001702	005212				INC	(R2)	; SET MSGTYP TO FATAL ERROR	
586	001704	000000				HALT		; HIGH TO LOW IN SAME .WORD FAILED	
587								; TO SCOPE REPLACE HALT W/ 240	
588								; AND REPLACE NEXT INST W/ 700	
589									
590	001706	126767	176730	176725	65:	CMPB	K10, K7+1		
591	001714	001005				BNE	TST4		
592	001716	012737	000025	000402		MOV	#25, 3#SFATAL	; MOVE TO MAILBOX # ***** 25 *****	
593	001724	005212				INC	(R2)	; SET MSGTYP TO FATAL ERROR	
594	001726	000000				HALT		; .EVEN TO ODD FAILED, OR WRONG \$TESTN, OR WRONG \$TESTN	
595								; TO SCOPE REPLACE HALT W/ 240	
596								; AND REPLACE NEXT INST W/ 667	



F02

```

597
598
599
600
601 001730 005237 000404
602 001734 022737 000004 000404
603 001742 001070
604 001744 000277
605 001746 005067 011144
606 001752 106467 011140
607 001756 103005
608 001760 012737 000026 000402
609 001766 005212
610 001770 000000
611
612
613 001772
614 001772 102005
615 001774 012737 000027 000402
616 002002 005212
617 002004 000000
618
619
620 002006
621 002006 001005
622 002010 012737 000030 000402
623 002016 005212
624 002020 000000
625
626
627 002022
628 002022 100005
629 002024 012737 000031 000402
630 002032 005212
631 002034 000000
632
633
634
635 002036 000257
636 002040 106767 011052
637 002044 052767 000017 011044
638 002052 106467 011040
639
640 002056 103405
641 002060 012737 000032 000402
642 002066 005212
643 002070 000000
644
645
646 002072
647 002072 102405
648 002074 012737 000033 000402
649 002102 005212
650 002104 000000
651
652

```

```

*****
;TEST 4 TEST THE CC BITS
*****
TST4:  INC      @#STESTN      ;UPDATE TEST NUMBER
        CMP      #4,@#STESTN  ;SEQUENCE ERROR?
        BNE     TST5-12 ;BR TO ERROR HALT ON SEQ ERROR
        SCC     ;SET STATUS
        CLR     STATUS        ;CLEAR STATUS
        MTPS   STATUS
        BCC    1$
        MOV     #26,@#$FATAL  ;MOVE TO MAILBOX # ***** 26 *****
        INC    (R2)           ;SET MSGTYP TO FATAL ERROR
        HALT   ;C NOT CLEAR
                ; TO SCOPE REPLACE HALT W/ 240
                ; AND REPLACE NEXT INST W/ 764
1$:    BVC     2$
        MOV     #27,@#$FATAL  ;MOVE TO MAILBOX # ***** 27 *****
        INC    (R2)           ;SET MSGTYP TO FATAL ERROR
        HALT   ;V NOT CLEAR
                ; TO SCOPE REPLACE HALT W/ 240
                ; AND REPLACE NEXT INST W/ 756
2$:    BNE     3$
        MOV     #30,@#$FATAL  ;MOVE TO MAILBOX # ***** 30 *****
        INC    (R2)           ;SET MSGTYP TO FATAL ERROR
        HALT   ;Z NOT CLEAR
                ; TO SCOPE REPLACE HALT W/ 240
                ; AND REPLACE NEXT INST W/ 750
3$:    BPL     4$
        MOV     #31,@#$FATAL  ;MOVE TO MAILBOX # ***** 31 *****
        INC    (R2)           ;SET MSGTYP TO FATAL ERROR
        HALT   ;N NOT CLEAR
                ; TO SCOPE REPLACE HALT W/ 240
                ; AND REPLACE NEXT INST W/ 742
4$:    CCC     ;CLEAR CONDITION CODES
        MFPS   STATUS
        BIS    #17,STATUS    ;SET STATUS TO ONES
        MTPS   STATUS
        BCS    5$
        MOV     #32,@#$FATAL  ;MOVE TO MAILBOX # ***** 32 *****
        INC    (R2)           ;SET MSGTYP TO FATAL ERROR
        HALT   ;C NOT SET
                ; TO SCOPE REPLACE HALT W/ 240
                ; AND REPLACE NEXT INST W/ 724
5$:    BVS     6$
        MOV     #33,@#$FATAL  ;MOVE TO MAILBOX # ***** 33 *****
        INC    (R2)           ;SET MSGTYP TO FATAL ERROR
        HALT   ;V NOT SET
                ; TO SCOPE REPLACE HALT W/ 240
                ; AND REPLACE NEXT INST W/ 716

```

G02

MAIN. MACY11 27(1006) 17-FEB-77 15:39 PAGE 19  
DVKADB.P11 17-FEB-77 15:34 T4 TEST THE CC BITS

SEQ 0021

653	002106				6\$:					
654	002106	001405				BEG	7\$			
655	002110	012737	000034	000402		MOV	#34, @#\$FATAL	:	MOVE TO MAILBOX # ***** 34 *****	
656	002116	005212				INC	(R2)	:	SET MSGTYP TO FATAL ERROR	
657	002120	000000				HALT		:	Z NOT SET	
658								:	TO SCOPE REPLACE HALT W/ 240	
659								:	AND REPLACE NEXT INST W/ 710	
660	002122				7\$:					
661	002122	100405				BMI	TST5			
662	002124	012737	000035	000402		MOV	#35, @#\$FATAL	:	MOVE TO MAILBOX # ***** 35 *****	
663	002132	005212				INC	(R2)	:	SET MSGTYP TO FATAL ERROR	
664	002134	000000				HALT		:	N NOT SET, OR WRONG \$TESTN	
665								:	TO SCOPE REPLACE HALT W/ 240	
666								:	AND REPLACE NEXT INST W/ 702	



```

667
668
669
670
671 002136 005237 000404
672 002142 022737 000005 000404
673 002150 001006
674 002152 012706 000500
675 002156 012767 002200 175624
676 002164 000007
677 002166 012737 000036 000402
678 002174 005212
679 002176 000000
680
681
682 002200
683
684
685
686 002200 005237 000404
687 002204 022737 000006 000404
688 002212 001011
689 002214 012706 000500
690 002220 012767 002230 175562
691 002226 000007
692 002230 020627 000474
693 002234 001405
694 002236 012737 000037 000402
695 002244 005212
696 002246 000000
697
698
;*****
;TEST 5 TEST THAT A TRAP OCCURES ON A RESERVED INSTRUCTION
;*****
TST5: INC @#STESTN ;UPDATE TEST NUMBER
      CMP #5,@#STESTN ;SEQUENCE ERROR?
      BNE TST6-12 ;BR TO ERROR HALT ON SEQ ERROR
      MOV #BUFF,SP ;STACK POINTER SETUP
      MOV #RETA,RTRAP ;RETURN LOCATION
      TRAPA ;RESERVED INSTRUCTION, SHOULD TRAP
      MOV #36,@#SFATAL ;MOVE TO MAILBOX # ***** 36 *****
      INC (R2) ;SET MSGTYP TO FATAL ERROR
      HALT ;DID NOT TRAP OR WRONG $TESTN
           ; TO SCOPE REPLACE HALT W/ 240
           ; AND REPLACE NEXT INST W/ 764

RETA:
;*****
;TEST 6 TEST DECREMENT OF STACK POINTER ON A TRAP OPERATION
;*****
TST6: INC @#STESTN ;UPDATE TEST NUMBER
      CMP #6,@#STESTN ;SEQUENCE ERROR?
      BNE TST7-12 ;BR TO ERROR HALT ON SEQ ERROR
      MOV #BUFF,SP ;STACK POINTER SETUP
      MOV #RETB,RTRAP ;RETURN POINTER
      TRAPA ;RESERVED INSTRUCTION
      RETB: CMP SP,#BUFF-4 ;TEST DECREMENT OF SP
            BEQ TST7
            MOV #37,@#SFATAL ;MOVE TO MAILBOX # ***** 37 *****
            INC (R2) ;SET MSGTYP TO FATAL ERROR
            HALT ;NOT DECREMENTED TWO WORDS, OR WRONG $TESTN
                  ; TO SCOPE REPLACE HALT W/ 240
                  ; AND REPLACE NEXT INST W/ 761
    
```

```

699
700
701
702
703 002250 005237 000404
704 002254 022737 000007 000404
705 002262 001012
706 002264 012706 000500
707 002270 012767 002300 175512
708 002276 000007
709 002300 022767 002300 176166
710 002306 001405
711 002310 012737 000040 000402
712 002316 005212
713 002320 000000
714
715
716
717
718
719 002322 005237 000404
720 002326 022737 000010 000404
721 002334 001044
722 002336 012706 000500
723 002342 012767 002364 175440
724 002350 005067 010542
725 002354 106467 010536
726 002360 000257
727 002362 000007
728 002364 026727 176106 000000
729 002372 001405
730 002374 012737 000041 000402
731 002402 005212
732 002404 000000
733
734
735 002406 012706 000500
736 002412 012767 002436 175370
737 002420 012767 000357 010470
738 002426 106467 010464
739 002432 000277
740 002434 000007
741 002436 026727 176034 000357
742 002444 001405
743 002446 012737 000042 000402
744 002454 005212
745 002456 000000
746
747

```

```

;*****
;TEST 7 TEST THAT PROPER P.C. IS SAVED
;*****
TST7: INC @#STESTN ;UPDATE TEST NUMBER
      CMP #7,@#STESTN ;SEQUENCE ERROR?
      BNE TST10-12 ;BR TO ERROR HALT ON SEQ ERROR
      MOV #BUFF,SP ;STACK POINTER SETUP
      MOV #RETC,RTRAP ;RETURN FROM TRAP POINTER
INSTC: TRAPA ;TRAP ON THIS INSTRUCTION
RETC:  CMP #.,BUFF-4 ;CHECK FOR INCREMENTED P.C.
      BEQ TST10
      MOV #40,@#SFATAL ;MOVE TO MAILBOX # ***** 40 *****
      INC (R2) ;SET MSGTYP TO FATAL ERROR
      HALT ;INCORRECT P.C. OR WRONG $TESTN
          ; TO SCOPE REPLACE HALT W/ 240
          ; AND REPLACE NEXT INST W/ 760
;*****
;TEST 10 TEST THAT "OLD" STATUS AND PRIORITY ARE PLACED ON STACK
;*****
TST10: INC @#STESTN ;UPDATE TEST NUMBER
      CMP #10,@#STESTN ;SEQUENCE ERROR?
      BNE TST11-12 ;BR TO ERROR HALT ON SEQ ERROR
      MOV #BUFF,SP ;SET UP
      MOV #RETD,RTRAP ;SET UP
      CLR STATUS ;CLEAR STATUS AND PRIORITY
      MTPS STATUS
      CCC
      TRAPA ;TRAP
RETD:  CMP BUFF-2,#0 ;TEST THAT OLD STATUS WENT TO STACK
      BEQ 1$
      MOV #41,@#SFATAL ;MOVE TO MAILBOX # ***** 41 *****
      INC (R2) ;SET MSGTYP TO FATAL ERROR
      HALT ;INCORRECT STATUS
          ; TO SCOPE REPLACE HALT W/ 240
          ; AND REPLACE NEXT INST W/ 753
          ; SET UP
          ; SET UP
          ; SET PRIORITY
1$:    MOV #BUFF,SP ;SET STATUS
      MOV #RETE,RTRAP ;TRAP
      MOV #357,STATUS ;COMPARES STATUS ON STACK
      MTPS STATUS
      SCC
      TRAPA
RETE:  CMP BUFF-2,#357
      BEQ TST11
      MOV #42,@#SFATAL ;MOVE TO MAILBOX # ***** 42 *****
      INC (R2) ;SET MSGTYP TO FATAL ERROR
      HALT ;INCORRECT STATUS ON STACK, OR WRONG $TESTN
          ; TO SCOPE REPLACE HALT W/ 240
          ; AND REPLACE NEXT INST W/ 726

```



# J02

MAIN. MACY11 27(1006) 17-FEB-77 15:39 PAGE 22  
 DVKADB.P11 17-FEB-77 15:34 T10

TEST THAT "OLD" STATUS AND PRIORITY ARE PLACED ON STACK

SEG 0024

```

748
749
750 ;*****
751 ;TEST 11 TEST THAT "NEW" STATUS IS CORRECT
752 ;*****
752 002460 005237 000404 000404 TST11: INC @#STESTN ;UPDATE TEST NUMBER
753 002464 022737 000011 000404 CMP #11,@#STESTN ;SEQUENCE ERROR?
754 002472 001125 BNE RSTP1 ;BR TO ERROR HALT ON SEQ ERROR
755 002474 012706 000500 MOV #BUFF,SP
756 002500 012767 002514 175302 MOV #RETG,RTRAP
757 002506 005067 175300 CLR RTRAP+2 ;CLEAR FUTURE PRIORITY AND CC
758 002512 000007 TRAPA
759 002514 RETF:
760 002514 100005 BPL 1$
761 002516 012737 000043 000402 MOV #43,@#SFATAL ;MOVE TO MAILBOX # ***** 43 *****
762 002524 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
763 002526 000000 HALT ;C NOT CLEARED
764 ; TO SCOPE REPLACE HALT W/ 240
765 ; AND REPLACE NEXT INST W/ 761
766 002530 1$:
767 002530 001005 BNE 2$
768 002532 012737 000044 000402 MOV #44,@#SFATAL ;MOVE TO MAILBOX # ***** 44 *****
769 002540 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
770 002542 000000 HALT ;Z NOT CLEARED
771 ; TO SCOPE REPLACE HALT W/ 240
772 ; AND REPLACE NEXT INST W/ 753
773 002544 2$:
774 002544 102005 BVC 3$
775 002546 012737 000045 000402 MOV #45,@#SFATAL ;MOVE TO MAILBOX # ***** 45 *****
776 002554 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
777 002556 000000 HALT ;V NOT CLEARED
778 ; TO SCOPE REPLACE HALT W/ 240
779 ; AND REPLACE NEXT INST W/ 745
780 002560 3$:
781 002560 103005 BCC 4$
782 002562 012737 000046 000402 MOV #46,@#SFATAL ;MOVE TO MAILBOX # ***** 46 *****
783 002570 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
784 002572 000000 HALT ;C NOT CLEARED
785 ; TO SCOPE REPLACE HALT W/ 240
786 ; AND REPLACE NEXT INST W/ 737
787 002574 106767 010316 010316 4$: MFPS STATUS
788 002600 032767 000340 010310 BIT #340,STATUS ;TEST PRIORITY
789 002606 001405 BEQ 5$
790 002610 012737 000047 000402 MOV #47,@#SFATAL ;MOVE TO MAILBOX # ***** 47 *****
791 002616 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
792 002620 000000 HALT ;PRIORITY NOT ZERO
793 ; TO SCOPE REPLACE HALT W/ 240
794 ; AND REPLACE NEXT INST W/ 724
795 002622 012706 000500 5$: MOV #BUFF,SP
796 002626 012767 002644 175154 MOV #RETG,RTRAP
797 002634 012767 000357 175150 MOV #357,RTRAP+2 ;SET NEW "CC" AND PRIORITY
798 002642 000007 TRAPA ;TRAP HERE
799 002644 RETG:
800 002644 100405 BMI 1$
801 002646 012737 000050 000402 MOV #50,@#SFATAL ;MOVE TO MAILBOX # ***** 50 *****
802 002654 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
803 002656 000000 HALT ;N NOT SET
  
```

# K02

MAIN. MACY11 27(1006) 17-FEB-77 15:39 PAGE 23  
 DVKADB.P11 17-FEB-77 15:34 T11 TEST

THAT "NEW" STATUS IS CORRECT

SEG 0025

804									; TO SCOPE REPLACE HALT W/ 240
805									; AND REPLACE NEXT INST W/ 705
806	002660				1\$:				
807	002660	001405				BEQ	2\$		
808	002662	012737	000051	000402		MOV	#51, 2\$FATAL	; MOVE TO MAILBOX # ***** 51 *****	
809	002670	005212				INC	(R2)	; SET MSGTYP TO FATAL ERROR	
810	002672	000000				HALT		; Z NOT SET	
811								; TO SCOPE REPLACE HALT W/ 240	
812								; AND REPLACE NEXT INST W/ 677	
813	002674				2\$:				
814	002674	102405				BVS	3\$		
815	002676	012737	000052	000402		MOV	#52, 2\$FATAL	; MOVE TO MAILBOX # ***** 52 *****	
816	002704	005212				INC	(R2)	; SET MSGTYP TO FATAL ERROR	
817	002706	000000				HALT		; V NOT SET	
818								; TO SCOPE REPLACE HALT W/ 240	
819								; AND REPLACE NEXT INST W/ 671	
820	002710				3\$:				
821	002710	103405				BCS	4\$		
822	002712	012737	000053	000402		MOV	#53, 2\$FATAL	; MOVE TO MAILBOX # ***** 53 *****	
823	002720	005212				INC	(R2)	; SET MSGTYP TO FATAL ERROR	
824	002722	000000				HALT		; C NOT SET	
825								; TO SCOPE REPLACE HALT W/ 240	
826								; AND REPLACE NEXT INST W/ 663	
827	002724	106767	010166		4\$:	MFPS	STATUS		
828	002730	016706	010162			MOV	STATUS, SP		
829	002734	042706	000017			BIC	#17, SP		
830	002740	022706	000340			CMP	#340, SP		
831	002744	001405				BEQ	RST1		
832	002746				RSTP1:				
833	002746	012737	000054	000402		MOV	#54, 2\$FATAL	; MOVE TO MAILBOX # ***** 54 *****	
834	002754	005212				INC	(R2)	; SET MSGTYP TO FATAL ERROR	
835	002756	000000				HALT		; PRIORITY WAS CHANGED, OR WRONG \$TESTN	
836								; TO SCOPE REPLACE HALT W/ 240	
837								; AND REPLACE NEXT INST W/ 645	
838	002760	012767	000012	175022	RST1:	MOV	#12, 10		
839	002766	005067	175020			CLR	12		



```

840
841 ;*****
842 ;TEST 12 TEST THAT A TRAP OCCURES FOR A "TRAP" INSTRUCTION
843 ;*****
844 002772 005237 000404 TST12: INC @#STESTN ;UPDATE TEST NUMBER
845 002776 022737 000012 000404 CMP #12,@#STESTN ;SEQUENCE ERROR?
846 003004 001006 BNE TST13-12 ;BR TO ERROR HALT ON SEQ ERROR
847 003006 012706 000500 MOV #BUFF,SP ;STACK POINTER SETUP
848 003012 012767 003034 175014 MOV #RETA1,RTRAP1 ;RETURN LOCATION
849 003020 104400 TRAP ;RESERVED INSTRUCTION, SHOULD TRAP
850 003022 012737 000055 000402 MOV #55,@#SFATAL ;MOVE TO MAILBOX # ***** 55 *****
851 003030 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
852 003032 000000 HALT ;DID NOT TRAP,OR WRONG $STESN
853 ; TO SCOPE REPLACE HALT W/ 240
854 ; AND REPLACE NEXT INST W/ 764
855 003034 RETA1:
856 ;*****
857 ;TEST 13 TEST DECREMENT OF STACK POINTER ON A TRAP OPERATION
858 ;*****
859 003034 005237 000404 TST13: INC @#STESTN ;UPDATE TEST NUMBER
860 003040 022737 000013 000404 CMP #13,@#STESTN ;SEQUENCE ERROR?
861 003046 001011 BNE TST14-12 ;BR TO ERROR HALT ON SEQ ERROR
862 003050 012706 000500 MOV #BUFF,SP ;STACK POINTER SETUP
863 003054 012767 003064 174752 MOV #RETB1,RTRAP1 ;RETURN POINTER
864 003062 104400 TRAP ;RESERVED INSTRUCTION
865 003064 020627 000474 RETB1: CMP SP,#BUFF-4 ;TEST DECREMENT OF SP
866 003070 001405 BEQ TST14
867 003072 012737 000056 000402 MOV #56,@#SFATAL ;MOVE TO MAILBOX # ***** 56 *****
868 003100 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
869 003102 000000 HALT ;NOT DECREMENTED TWO WORDS,OR WRONG $STESN
870 ; TO SCOPE REPLACE HALT W/ 240
871 ; AND REPLACE NEXT INST W/ 761
872 ;*****
873 ;TEST 14 TEST THAT PROPER P.C. IS SAVED
874 ;*****
875 003104 005237 000404 TST14: INC @#STESTN ;UPDATE TEST NUMBER
876 003110 022737 000014 000404 CMP #14,@#STESTN ;SEQUENCE ERROR?
877 003116 001012 BNE TST15-12 ;BR TO ERROR HALT ON SEQ ERROR
878 003120 012706 000500 MOV #BUFF,SP ;STACK POINTER SETUP
879 003124 012767 003134 174702 MOV #RETC1,RTRAP1 ;RETURN FROM TRAP POINTER
880 003132 104400 TRAP ;TRAP ON THIS INSTRUCTION
881 003134 022767 003134 175332 RETC1: CMP #,BUFF-4 ;CHECK INCREMENTED P.C.
882 003142 001405 BEQ TST15
883 003144 012737 000057 000402 MOV #57,@#SFATAL ;MOVE TO MAILBOX # ***** 57 *****
884 003152 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
885 003154 000000 HALT ;INCORRECT P.C. OR WRONG $STESN
886 ; TO SCOPE REPLACE HALT W/ 240
887 ; AND REPLACE NEXT INST W/ 760

```

M02

```

888
889
890 ;*****
891 ;TEST 15 TEST THAT "OLD" STATUS AND PRIORITY ARE PLACED ON STACK
892 ;*****
892 003156 005237 000404 TST15: INC @#STESTN ;UPDATE TEST NUMBER
893 003162 022737 000015 000404 CMP #15,@#STESTN ;SEQUENCE ERROR?
894 003170 001043 BNE TST16-12 ;BR TO ERROR HALT ON SEQ ERROR
895 003172 012706 000500 MOV #BUFF SP ;SET UP
896 003176 012767 003220 174630 MOV #RETD1,RTRAP1 ;SET UP
897 003204 005067 007706 CLR STATUS ;CLEAR STATUS AND PRIORITY
898 003210 106467 007702 MTPS STATUS
899 003214 000257 CCC
900 003216 104400 TRAP ;TRAP
901 003220 026727 175252 000000 RETD1: CMP BUFF-2,#0 ;TEST THAT OLD STATUS WENT TO STACK
902 003226 001405 BEQ 1$
903 003230 012737 000060 000402 MOV #60,@#$FATAL ;MOVE TO MAILBOX # ***** 60 *****
904 003236 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
905 003240 000000 HALT ;INCORRECT STATUS
906 ; TO SCOPE REPLACE HALT W/ 240
907 ; AND REPLACE NEXT INST W/ 753
908 003242 012706 000500 1$: MOV #BUFF SP ;SET UP
909 003246 012767 003270 174560 MOV #RETE1,RTRAP1 ;SET UP
910 003254 012767 000357 007634 MOV #357,STATUS ;SET PRIORITY
911 003262 106467 007630 MTPS STATUS
912 003266 104400 TRAP ;SET CC
913 003270 026727 175202 000357 RETE1: CMP BUFF-2,#357 ;COMPARES STATUS ON STACK
914 003276 001405 BEQ TST16
915 003300 012737 000061 000402 MOV #61,@#$FATAL ;MOVE TO MAILBOX # ***** 61 *****
916 003306 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
917 003310 000000 HALT ;INCORRECT STATUS ON STACK
918 ; TO SCOPE REPLACE HALT W/ 240
919 ; AND REPLACE NEXT INST W/ 727

```



```

920
921
922
923
924 003312 005237 000404
925 003316 022737 000016 000404
926 003324 001125
927 003326 012706 000500
928 003332 012767 003346 174474
929 003340 005067 174472
930 003344 104400
931 003346
932 003346 100005
933 003350 012737 000062 000402
934 003356 005212
935 003360 000000
936
937
938 003362
939 003362 001005
940 003364 012737 000063 000402
941 003372 005212
942 003374 000000
943
944
945 003376
946 003376 102005
947 003400 012737 000064 000402
948 003406 005212
949 003410 000000
950
951
952 003412
953 003412 103005
954 003414 012737 000065 000402
955 003422 005212
956 003424 000000
957
958
959 003426 106767 007464
960 003432 032767 000340 007456
961 003440 001405
962 003442 012737 000066 000402
963 003450 005212
964 003452 000000
965
966
967 003454 012706 000500
968 003460 012767 003476 174346
969 003466 012767 000357 174342
970 003474 104400
971 003476
972 003476 100405
973 003500 012737 000067 000402
974 003506 005212
975 003510 000000

```

```

;*****
;TEST 16 TEST THAT "NEW" STATUS IS CORRECT
;*****
TST16: INC @#STESTN ;UPDATE TEST NUMBER
CMP #16,@#STESTN ;SEQUENCE ERROR?
BNE TST17-12 ;BR TO ERROR HALT ON SEQ ERROR
MOV #BUFF,SP
MOV #RETF1,RTRAP1
CLR RTRAP1+2 ;CLEAR FUTURE PRIORITY AND CC
TRAP

RETF1:
BPL 1$
MOV #62,@#$FATAL ;MOVE TO MAILBOX # ***** 62 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;C NOT CLEARED
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 761

1$:
BNE 2$
MOV #63,@#$FATAL ;MOVE TO MAILBOX # ***** 63 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;Z NOT CLEARED
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 753

2$:
BVC 3$
MOV #64,@#$FATAL ;MOVE TO MAILBOX # ***** 64 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;V NOT CLEARED
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 745

3$:
BCC 4$
MOV #65,@#$FATAL ;MOVE TO MAILBOX # ***** 65 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;C NOT CLEARED
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 737

4$:
MFPS STATUS
BIT #340,STATUS ;TEST PRIORITY
BEQ 5$
MOV #66,@#$FATAL ;MOVE TO MAILBOX # ***** 66 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;PRIORITY NOT ZERO
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 724

5$:
MOV #BUFF,SP
MOV #RETF1,RTRAP1
MOV #357,RTRAP1+2 ;SET NEW "CC" AND PRIORITY
TRAP ;TRAP HERE

RETF1:
BMI 1$
MOV #67,@#$FATAL ;MOVE TO MAILBOX # ***** 67 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;N NOT SET

```





```

1009
1010
1011
1012
1013 003612 005237 000404
1014 003616 022737 000017 000404
1015 003624 001011
1016 003626 012767 104400 000012
1017 003634 012767 003662 174172
1018 003642 012706 000500
1019 003646 104400
1020 003650
1021 003650 012737 000074 000402
1022 003656 005212
1023 003660 000000
1024
1025
1026 003662 005267 177760
1027 003666 022767 104777 177752
1028 003674 103362
1029 003676 012767 000036 174130
1030 003704 005067 174126
1031
1032
1033
1034 003710 005237 000404
1035 003714 022737 000020 000404
1036 003722 001006
1037 003724 012706 000500
1038 003730 012767 003752 174062
1039 003736 000004
1040 003740 012737 000075 000402
1041 003746 005212
1042 003750 000000
1043
1044
1045 003752
1046
1047
1048
1049 003752 005237 000404
1050 003756 022737 000021 000404
1051 003764 001011
1052 003766 012706 000500
1053 003772 012767 004002 174020
1054 004000 000004
1055 004002 020627 000474
1056 004006 001405
1057 004010 012737 000076 000402
1058 004016 005212
1059 004020 000000
1060
1061

;*****
;TEST 17 TEST THAT ALL COMBINATION OF "TRAP" WILL CAUSE A TRAP
;*****
TST17: INC @#STESTN ;UPDATE TEST NUMBER
        CMP #17,@#STESTN ;SEQUENCE ERROR?
        BNE RB1AA ;BR TO ERROR HALT ON SEQ ERROR
        MOV #TRAP,RB1 ;INITIALIZE BASE TRAP INSTRUCTION
        MOV #RA1,34 ;RETURN FROM TRAP TO RA1
RC1: MOV #BUFF,SP ;SET UP STACK POINTER
RB1: TRAP ;TRAP INST WILL BE MODIFIED TO TRAP+377
RB1AA: MOV #74,@#SFATAL ;MOVE TO MAILBOX # ***** 74 *****
        INC (R2) ;SET MSGTYP TO FATAL ERROR
        HALT ;PREVIOUS INST FAILED TO TRAP OR WRONG $TESTN
        ; TO SCOPE REPLACE HALT W/ 240
        ; AND REPLACE NEXT INST W/ 761

RA1: INC RB1
      CMP #104777,RB1 ;TRAP+377 TO UPPER LIMIT
      BHIS RC1 ;HAVE WE TESTED ALL
      MOV #36,34
      CLR 36

;*****
;TEST 20 TEST THAT A TRAP OCCURES ON AN "IOT" INSTRUCTION
;*****
TST20: INC @#STESTN ;UPDATE TEST NUMBER
        CMP #20,@#STESTN ;SEQUENCE ERROR?
        BNE TST21-12 ;BR TO ERROR HALT ON SEQ ERROR
        MOV #BUFF,SP ;STACK POINTER SETUP
        MOV #RETA2,RTRAP2 ;RETURN LOCATION
        IOT ;RESERVE INSTRUCTION, SHOULD TRAP
        MOV #75,@#SFATAL ;MOVE TO MAILBOX # ***** 75 *****
        INC (R2) ;SET MSGTYP TO FATAL ERROR
        HALT ;IOT DID NOT TRAP OR WRONG $TESTN
        ; TO SCOPE REPLACE HALT W/ 240
        ; AND REPLACE NEXT INST W/ 764

RETA2:

;*****
;TEST 21 TEST DECREMENT OF STACK POINTER ON A TRAP OPERATION
;*****
TST21: INC @#STESTN ;UPDATE TEST NUMBER
        CMP #21,@#STESTN ;SEQUENCE ERROR?
        BNE TST22-12 ;BR TO ERROR HALT ON SEQ ERROR
        MOV #BUFF,SP ;STACK POINTER SETUP
        MOV #RETB2,RTRAP2 ;RETURN POINTER
        IOT ;RESERVED INSTRUCTION
RETB2: CMP SP,#BUFF-4 ;TEST DECREMENT OF SP
        BEQ TST22
        MOV #76,@#SFATAL ;MOVE TO MAILBOX # ***** 76 *****
        INC (R2) ;SET MSGTYP TO FATAL ERROR
        HALT ;NOT DECREMENTED TWO WORDS,OR WRONG $TESTN
        ; TO SCOPE REPLACE HALT W/ 240
        ; AND REPLACE NEXT INST W/ 761

```

```

1062
1063
1064
1065
1066 004022 005237 000404
1067 004026 022737 000022 000404
1068 004034 001012
1069 004036 012706 000500
1070 004042 012767 004052 173750
1071 004050 000004
1072 004052 022767 004052 174414 RETC2:
1073 004060 001405
1074 004062 012737 000077 000402
1075 004070 005212
1076 004072 000000
1077
1078
1079
1080
1081
1082 004074 005237 000404
1083 004100 022737 000023 000404
1084 004106 001044
1085 004110 012706 000500
1086 004114 012767 004136 173676
1087 004122 005067 006770
1088 004126 106467 006764
1089 004132 000257
1090 004134 000004
1091 004136 026727 174334 000000 RETD2:
1092 004144 001405
1093 004146 012737 000100 000402
1094 004154 005212
1095 004156 000000
1096
1097
1098 004160 012706 000500
1099 004164 012767 004210 173626
1100 004172 012767 000357 006716
1101 004200 106467 006712
1102 004204 000277
1103 004206 000004
1104 004210 026727 174262 000357 RETE2:
1105 004216 001405
1106 004220 012737 000101 000402
1107 004226 005212
1108 004230 000000
1109
1110

```

```

;*****
;TEST 22 TEST THAT PROPER P.C. IS SAVED
;*****
↑ST22: INC @STESTN ;UPDATE TEST NUMBER
CMP #22,@STESTN ;SEQUENCE ERROR?
BNE TST23-12 ;BR TO ERROR HALT ON SEQ ERROR
MOV #BUFF,SP ;STACK POINTER SETUP
MOV #RETC2,RTRAP2 ;RETURN FROM TRAP POINTER
IOT ;TRAP ON THIS INSTRUCTION
RETC2: CMP #,BUFF-4 ;CHECK FOR INCREMENTED P.C.
BEQ TST23
MOV #77,@SFATAL ;MOVE TO MAILBOX # ***** 77 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;INCORRECT P.C. OR WRONG $TESTN
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 760
;*****
;TEST 23 TEST THAT "OLD" STATUS AND PRIORITY ARE PLACED ON STACK
;*****
↑ST23: INC @STESTN ;UPDATE TEST NUMBER
CMP #23,@STESTN ;SEQUENCE ERROR?
BNE TST24-12 ;BR TO ERROR HALT ON SEQ ERROR
MOV #BUFF,SP ;SET UP
MOV #RETD2,RTRAP2 ;SET UP
CLR STATUS ;CLEAR STATUS AND PRIORITY
MTPS STATUS
CCC
IOT ;TRAP
RETD2: CMP BUFF-2,#0 ;TEST THAT OLD STATUS WENT TO STACK
BEQ 1$
MOV #100,@SFATAL ;MOVE TO MAILBOX # ***** 100 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;INCORRECT STATUS
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 753
1$: MOV #BUFF,SP ;SET UP
MOV #RETE2,RTRAP2 ;SET UP
MOV #357,STATUS ;SET PRIORITY
MTPS STATUS
SCC ;SET CC
IOT ;TRAP
RETE2: CMP BUFF-2,#357 ;COMPARES STATUS ON STACK
BEQ TST24
MOV #101,@SFATAL ;MOVE TO MAILBOX # ***** 101 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;INCORRECT STATUS ON STACK, OR WRONG $TESTN
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 726

```



# E03

MAIN. MACY11 27(1006) 17-FEB-77 15:39 PAGE 30  
 DVKADB.P11 17-FEB-77 15:34 T23

TEST THAT "OLD" STATUS AND PRIORITY ARE PLACED ON STACK

SEQ 0032

```

1111
1112
1113
1114
1115 004232 005237 000404
1116 004236 022737 000024 000404
1117 004244 001125
1118 004246 012706 000500
1119 004252 012767 004266 173540
1120 004260 005067 173536
1121 004264 000004
1122 004266
1123 004266 100005
1124 004270 012737 000102 000402
1125 004276 005212
1126 004300 000000
1127
1128
1129 004302
1130 004302 001005
1131 004304 012737 000103 000402
1132 004312 005212
1133 004314 000000
1134
1135
1136 004316
1137 004316 102005
1138 004320 012737 000104 000402
1139 004326 005212
1140 004330 000000
1141
1142
1143 004332
1144 004332 103005
1145 004334 012737 000105 000402
1146 004342 005212
1147 004344 000000
1148
1149
1150 004346 106767 006544
1151 004352 032767 000340 006536
1152 004360 001405
1153 004362 012737 000106 000402
1154 004370 005212
1155 004372 000000
1156
1157
1158 004374 012706 000500
1159 004400 012767 004416 173412
1160 004406 012767 000357 173406
1161 004414 000004
1162 004416
1163 004416 100405
1164 004420 012737 000107 000402
1165 004426 005212
1166 004430 000000

```

```

*****
;TEST 24 TEST THAT "NEW" STATUS IS CORRECT
*****
†ST24: INC @#STESTN ;UPDATE TEST NUMBER
        CMP #24,@#STESTN ;SEQUENCE ERROR?
        BNE STP ;BR TO ERROR HALT ON SEQ ERROR
        MOV #BUFF,SP
        MOV #RETF2,RTRAP2
        CLR RTRAP2+2 ;CLEAR FUTURE PRIORITY AND CC
        IOT
RETF2: BPL 1$
        MOV #102,@#SFATAL ;MOVE TO MAILBOX # ***** 102 *****
        INC (R2) ;SET MSGTYP TO FATAL ERROR
        HALT ;C NOT CLEARED
        ; TO SCOPE REPLACE HALT W/ 240
        ; AND REPLACE NEXT INST W/ 761
1$: BNE 2$
        MOV #103,@#SFATAL ;MOVE TO MAILBOX # ***** 103 *****
        INC (R2) ;SET MSGTYP TO FATAL ERROR
        HALT ;Z NOT CLEARED
        ; TO SCOPE REPLACE HALT W/ 240
        ; AND REPLACE NEXT INST W/ 753
2$: BVC 3$
        MOV #104,@#SFATAL ;MOVE TO MAILBOX # ***** 104 *****
        INC (R2) ;SET MSGTYP TO FATAL ERROR
        HALT ;V NOT CLEARED
        ; TO SCOPE REPLACE HALT W/ 240
        ; AND REPLACE NEXT INST W/ 745
3$: BCC 4$
        MOV #105,@#SFATAL ;MOVE TO MAILBOX # ***** 105 *****
        INC (R2) ;SET MSGTYP TO FATAL ERROR
        HALT ;C NOT CLEARED
        ; TO SCOPE REPLACE HALT W/ 240
        ; AND REPLACE NEXT INST W/ 737
4$: MFPS STATUS
        BIT #340,STATUS ;TEST PRIORITY
        BEQ 5$
        MOV #106,@#SFATAL ;MOVE TO MAILBOX # ***** 106 *****
        INC (R2) ;SET MSGTYP TO FATAL ERROR
        HALT ;PRIORITY NOT ZERO
        ; TO SCOPE REPLACE HALT W/ 240
        ; AND REPLACE NEXT INST W/ 724
5$: MOV #BUFF,SP
        MOV #RETF2,RTRAP2
        MOV #357,RTRAP2+2 ;SET NEW "CC" AND PRIORITY
        IOT ;TRAP HERE
RETF2: BMI 1$
        MOV #107,@#SFATAL ;MOVE TO MAILBOX # ***** 107 *****
        INC (R2) ;SET MSGTYP TO FATAL ERROR
        HALT ;N NOT SET

```

# F03

MAIN. MACY11 27(1006) 17-FEB-77 15:39 PAGE 31  
 DVKADB.P11 17-FEB-77 15:34 T24 TEST

THAT "NEW" STATUS IS CORRECT

SEG 0033

```

1167                                     ; TO SCOPE REPLACE HALT W/ 240
1168                                     ; AND REPLACE NEXT INST W/ 705
1169 004432                               1$:
1170 004432 001405                       BEQ      2$
1171 004434 012737 000110 000402       MOV      #110,@#$FATAL ; MOVE TO MAILBOX # ***** 110 *****
1172 004442 005212                       INC      (R2)           ; SET MSGTYP TO FATAL ERROR
1173 004444 000000                       HALT
1174                                     ; Z NOT SET
1175                                     ; TO SCOPE REPLACE HALT W/ 240
1176                                     ; AND REPLACE NEXT INST W/ 677
1176 004446                               2$:
1177 004446 102405                       BVS      3$
1178 004450 012737 000111 000402       MOV      #111,@#$FATAL ; MOVE TO MAILBOX # ***** 111 *****
1179 004456 005212                       INC      (R2)           ; SET MSGTYP TO FATAL ERROR
1180 004460 000000                       HALT
1181                                     ; V NOT SET
1182                                     ; TO SCOPE REPLACE HALT W/ 240
1183                                     ; AND REPLACE NEXT INST W/ 671
1183 004462                               3$:
1184 004462 103405                       BCS      4$
1185 004464 012737 000112 000402       MOV      #112,@#$FATAL ; MOVE TO MAILBOX # ***** 112 *****
1186 004472 005212                       INC      (R2)           ; SET MSGTYP TO FATAL ERROR
1187 004474 000000                       HALT
1188                                     ; C NOT SET
1189                                     ; TO SCOPE REPLACE HALT W/ 240
1190                                     ; AND REPLACE NEXT INST W/ 663
1190 004476 106767 006414 4$:          MFPS     STATUS
1191 004502 016706 006410                MOV      STATUS,SP
1192 004506 042706 000017                BIC      #17,SP
1193 004512 022706 000340                CMP      #340,SP
1194 004516 001405                       BEQ      STPA
1195 004520                               STP:
1196 004520 012737 000113 000402       MOV      #113,@#$FATAL ; MOVE TO MAILBOX # ***** 113 *****
1197 004526 005212                       INC      (R2)           ; SET MSGTYP TO FATAL ERROR
1198 004530 000000                       HALT
1199                                     ; PRIORITY WAS CHANGED, OR WRONG $TESTN
1200                                     ; TO SCOPE REPLACE HALT W/ 240
1201                                     ; AND REPLACE NEXT INST W/ 645
1201 004532 012767 000022 173260 STPA:  MOV      #22,20
1202 004540 005067 173256                CLR      22
  
```



```

1203
1204
1205 :*****
1206 :TEST 25 TEST THAT A TRAP OCCURS ON AN EMT RESTRICTED INSTRUCTION
1207 :*****
1207 004544 005237 000404 000404 †ST25: INC @#$TESTN ;UPDATE TEST NUMBER
1208 004550 022737 000025 000404 CMP #25,@#$TESTN ;SEQUENCE ERROR?
1209 004556 001006 BNE TST26-12 ;BR TO ERROR HALT ON SEQ ERROR
1210 004560 012706 000500 MOV #BUFF,SP ;STACK POINTER SETUP
1211 004564 012767 004606 173236 MOV #RETA3,RTRAP3 ;RETURN LOCATION
1212 004572 104000 EMT ;RESERVE INSTRUCTION, SHOULD TRAP
1213 004574 012737 000114 000402 MOV #114,@#$FATAL ;MOVE TO MAILBOX # ***** 114 *****
1214 004602 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
1215 004604 000000 HALT ;EMT DID NOT TRAP, OR WRONG $TESTN
1216 ; TO SCOPE REPLACE HALT W/ 240
1217 ; AND REPLACE NEXT INST W/ 764
1218 004606 RETA3:
1219 :*****
1220 :TEST 26 TEST DECREMENT OF STACK POINTER ON A TRAP OPERATION
1221 :*****
1222 004606 005237 000404 000404 †ST26: INC @#$TESTN ;UPDATE TEST NUMBER
1223 004612 022737 000026 000404 CMP #26,@#$TESTN ;SEQUENCE ERROR?
1224 004620 001011 BNE TST27-12 ;BR TO ERROR HALT ON SEQ ERROR
1225 004622 012706 000500 MOV #BUFF,SP ;STACK POINTER SETUP
1226 004626 012767 004636 173174 MOV #RETB3,RTRAP3 ;RETURN POINTER
1227 004634 104000 EMT ;RESERVED INSTRUCTION
1228 004636 020627 000474 RETB3: CMP SP,#BUFF-4 ;TEST DECREMENT OF SP
1229 004642 001405 BEQ TST27
1230 004644 012737 000115 000402 MOV #115,@#$FATAL ;MOVE TO MAILBOX # ***** 115 *****
1231 004652 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
1232 004654 000000 HALT ;NOT DECREMENTED TWO WORDS, OR WRONG $TESTN
1233 ; TO SCOPE REPLACE HALT W/ 240
1234 ; AND REPLACE NEXT INST W/ 761
1235 :*****
1236 :TEST 27 TEST THAT PROPER P.C. IS SAVED
1237 :*****
1238 004656 005237 000404 000404 †ST27: INC @#$TESTN ;UPDATE TEST NUMBER
1239 004662 022737 000027 000404 CMP #27,@#$TESTN ;SEQUENCE ERROR?
1240 004670 001012 BNE TST30-12 ;BR TO ERROR HALT ON SEQ ERROR
1241 004672 012706 000500 MOV #BUFF,SP ;STACK POINTER SETUP
1242 004676 012767 004706 173124 MOV #RETC3,RTRAP3 ;RETURN FROM TRAP POINTER
1243 004704 104000 EMT ;TRAP ON THIS INSTRUCTION
1244 004706 022767 004706 173560 RETC3: CMP #,BUFF-4 ;CHECK FOR INCREMENTED P.C.
1245 004714 001405 BEQ TST30
1246 004716 012737 000116 000402 MOV #116,@#$FATAL ;MOVE TO MAILBOX # ***** 116 *****
1247 004724 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
1248 004726 000000 HALT ;INCORRECT P.C. OR WRONG $TESTN
1249 ; TO SCOPE REPLACE HALT W/ 240
1250 ; AND REPLACE NEXT INST W/ 760

```

# H03

```

1251
1252
1253
1254
1255 004730 005237 000404
1256 004734 022737 000030 000404
1257 004742 001044
1258 004744 012706 000500
1259 004750 012767 004772 173052
1260 004756 005067 006134
1261 004762 106467 006130
1262 004766 000257
1263 004770 104000
1264 004772 026727 173500 000000 RETD3:
1265 005000 001405
1266 005002 012737 000117 000402
1267 005010 005212
1268 005012 000000
1269
1270
1271 005014 012706 000500 1$: MOV #BUFF,SP
1272 005020 012767 005044 173002 MOV #RETE3,RTRAP3
1273 005026 012767 000357 006062 MOV #357,STATUS
1274 005034 106467 006056 MTPS STATUS
1275 005040 000277 SCC
1276 005042 104000 EMT
1277 005044 026727 173426 000357 RETE3: CMP BUFF-2,#357
1278 005052 001405 BEQ TST31
1279 005054 012737 000120 000402 MOV #120,#$FATAL
1280 005062 005212 INC (R2)
1281 005064 000000 HALT
1282
1283

```

\*\*\*\*\*  
 :TEST 30 TEST THAT "OLD" STATUS AND PRIORITY ARE PLACED ON STACK  
 :\*\*\*\*\*  
 :ST30: INC @#STESTN ;UPDATE TEST NUMBER  
 CMP #30,@#STESTN ;SEQUENCE ERROR?  
 BNE TST31-12 ;BR TO ERROR HALT ON SEQ ERROR  
 MOV #BUFF,SP ;SET UP  
 MOV #RETD3,RTRAP3 ;SET UP  
 CLR STATUS ;CLEAR STATUS AND PRIORITY  
 MTPS STATUS  
 CCC  
 EMT ;TRAP  
 RETD3: CMP BUFF-2,#0 ;TEST THAT OLD STATUS WENT TO STACK  
 BEQ 1\$  
 MOV #117,@#\$FATAL ;MOVE TO MAILBOX # \*\*\*\*\* 117 \*\*\*\*\*  
 INC (R2) ;SET MSGTYP TO FATAL ERROR  
 HALT ;INCORRECT STATUS  
 ; TO SCOPE REPLACE HALT W/ 240  
 ; AND REPLACE NEXT INST W/ 753  
 1\$: MOV #BUFF,SP ;SET UP  
 MOV #RETE3,RTRAP3 ;SET UP  
 MOV #357,STATUS ;SET PRIORITY  
 MTPS STATUS  
 SCC ;SET CC  
 EMT ;TRAP  
 RETE3: CMP BUFF-2,#357 ;COMPARES STATUS ON STACK  
 BEQ TST31  
 MOV #120,#\$FATAL ;MOVE TO MAILBOX # \*\*\*\*\* 120 \*\*\*\*\*  
 INC (R2) ;SET MSGTYP TO FATAL ERROR  
 HALT ;INCORRECT STATUS ON STACK,OR WRONG \$TESTN  
 ; TO SCOPE REPLACE HALT W/ 240  
 ; AND REPLACE NEXT INST W/ 726



```

1284
1285
1286
1287
1288 005066 C05237 000404
1289 005072 022737 000031 000404
1290 005100 001125
1291 005102 012706 000500
1292 005106 012767 005122 172714
1293 005114 005067 172712
1294 005120 104000
1295 005122
1296 005122 100005
1297 005124 012737 000121 000402
1298 005132 005212
1299 005134 000000
1300
1301
1302 005136
1303 005136 001005
1304 005140 012737 000122 000402
1305 005146 005212
1306 005150 000000
1307
1308
1309 005152
1310 005152 102005
1311 005154 012737 000123 000402
1312 005162 005212
1313 005164 000000
1314
1315
1316 005166
1317 005166 103005
1318 005170 012737 000124 000402
1319 005176 005212
1320 005200 000000
1321
1322
1323 005202 106767 005710
1324 005206 032767 000340 005702
1325 005214 001405
1326 005216 012737 000125 000402
1327 005224 005212
1328 005226 000000
1329
1330
1331 005230 012706 000500
1332 005234 012767 005252 172566
1333 005242 012767 000357 172562
1334 005250 104000
1335 005252
1336 005252 100405
1337 005254 012737 000126 000402
1338 005262 005212
1339 005264 000000

```

```

:*****
:TEST 31 TEST THAT "NEW" STATUS IS CORRECT
:*****
TST31: INC @#STESTN ;UPDATE TEST NUMBER
CMP #31,@#STESTN ;SEQUENCE ERROR?
BNE TST32-12 ;BR TO ERROR HALT ON SEQ ERROR
MOV #BUFF,SP
MOV #RETF3,RTRAP3
CLR RTRAP3+2 ;CLEAR FUTURE PRIORITY AND CC
EMT
RETF3: ;TEST FOR "C" CLEARED
BPL 1$
MOV #121,@#$FATAL ;MOVE TO MAILBOX # ***** 121 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;^ NOT CLEARED
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 761
1$:
BNE 2$
MOV #122,@#$FATAL ;MOVE TO MAILBOX # ***** 122 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;Z NOT CLEARED
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 753
2$:
BVC 3$
MOV #123,@#$FATAL ;MOVE TO MAILBOX # ***** 123 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;V NOT CLEARED
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 745
3$:
BCC 4$
MOV #124,@#$FATAL ;MOVE TO MAILBOX # ***** 124 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;C NOT CLEARED
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 737
4$:
MFPS STATUS
BIT #340,STATUS ;TEST PRIORITY
BEQ 5$
MOV #125,@#$FATAL ;MOVE TO MAILBOX # ***** 125 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;PRIORITY NOT ZERO
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 724
5$:
MOV #BUFF,SP
MOV #RETF3,RTRAP3
MOV #357,RTRAP3+2 ;SET NEW "CC" AND PRIORITY
EMT ;TRAP HERE
RETF3:
BMI 1$
MOV #126,@#$FATAL ;MOVE TO MAILBOX # ***** 126 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;N NOT SET

```





K03

1373  
 1374  
 1375  
 1376  
 1377 005366 005237 000404  
 1378 005372 022737 000032 000404  
 1379 005400 001011  
 1380 005402 012767 104000 000012  
 1381 005410 012767 005436 172412  
 1382 005416 012706 000500  
 1383 005422 104000  
 1384 005424  
 1385 005424 012737 000133 000402  
 1386 005432 005212  
 1387 005434 000000  
 1388  
 1389  
 1390 005436 005267 177760  
 1391 005442 022767 104377 177752  
 1392 005450 103362  
 1393 005452 012767 000032 172350  
 1394 005460 005067 172346  
 1395  
 1396  
 1397  
 1398 005464 005237 000404  
 1399 005470 022737 000033 000404  
 1400 005476 001006  
 1401 005500 012706 000500  
 1402 005504 012767 005526 172302  
 1403 005512 000003  
 1404 005514 012737 000134 000402  
 1405 005522 005212  
 1406 005524 000000  
 1407  
 1408  
 1409 005526

```

;*****
;TEST 32      TEST THAT ALL COMBINATION OF EMT WILL CAUSE A TRAP
;*****
↑ST32:  INC      @#STESTN      ;UPDATE TEST NUMBER
        CMP      #32,@#STESTN  ;SEQUENCE ERROR?
        BNE     RBBB          ;BR TO ERROR HALT ON SEQ ERROR
        MOV     #EMT,RB       ;INITIALIZE BASE EMT INSTRUCTION
        MOV     #RA,30        ;RETURN FROM TRAP TO RA
RC:     MOV     #BUFF,SP      ;SET UP STACK POINTER
RB:     EMT                  ;TRAP INST. WILL BE MODIFIED TO EMT+377
RBBB:
        MOV     #133,@#SFATAL  ;MOVE TO MAILBOX # ***** 133 *****
        INC     (R2)           ;SET MSGTYP TO FATAL ERROR
        HALT                  ;PREVIOUS INST FAILED TO TRAP,OR WRONG $TESTN
                                ; TO SCOPE REPLACE HALT W/ 240
                                ; AND REPLACE NEXT INST W/ 761
RA:     INC     RB
        CMP     #104377,RB     ;EMT+377 TO EMT?
        BHIS   RC              ;HAVE WE TESTED ALL
        MOV     #32,30
        CLR    32              ;HALT
;*****
;TEST 33      TEST THAT A TRAP OCCURES ON AN "BPT" INSTRUCTION
;*****
↑ST33:  INC      @#STESTN      ;UPDATE TEST NUMBER
        CMP     #33,@#STESTN  ;SEQUENCE ERROR?
        BNE     TST34-12      ;BR TO ERROR HALT ON SEQ ERROR
        MOV     #BUFF,SP      ;STACK POINTER SETUP
        MOV     #RETA4,RTRAP4 ;RETURN LOCATION
        TRT    ;RESERVED INSTRUCTION, SHOULD TRAP
        MOV     #134,@#SFATAL  ;MOVE TO MAILBOX # ***** 134 *****
        INC     (R2)           ;SET MSGTYP TO FATAL ERROR
        HALT                  ;DID NOT TRAP,OR WRONG $TESTN
                                ; TO SCOPE REPLACE HALT W/ 240
                                ; AND REPLACE NEXT INST W/ 764
RETA4:

```

```

1410
1411
1412 ;*****
1413 ;TEST 34 TEST DECREMENT OF STACK POINTER ON A TRAP OPERATION
1414 ;*****
1414 005526 005237 000404 TST34: INC @#STESTN ;UPDATE TEST NUMBER
1415 005532 022737 000034 000404 CMP #34,@#STESTN ;SEQUENCE ERROR?
1416 005540 001011 BNE TST35-12 ;BR TO ERROR HALT ON SEQ ERROR
1417 005542 012706 000500 MOV #BUFF,SP ;STACK POINTER SETUP
1418 005546 012767 005556 172240 MOV #RETB4,RTRAP4 ;RETURN POINTER
1419 005554 000003 TRT ;RESERVED INSTRUCTION
1420 005556 020627 000474 RETB4: CMP SP,#BUFF-4 ;TEST DECREMENT OF SP
1421 005562 001405 BEQ TST35
1422 005564 012737 000135 000402 MOV #135,@#SFATAL ;MOVE TO MAILBOX # ***** 135 *****
1423 005572 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
1424 005574 000000 HALT ;NOT DECREMENTED TWO WORDS,OR WRONG STESTN
1425 ; TO SCOPE REPLACE HALT W/ 240
1426 ; AND REPLACE NEXT INST W/ 761
1427 ;*****
1428 ;TEST 35 TEST THAT PROPER P.C. IS SAVED
1429 ;*****
1430 005576 005237 000404 TST35: INC @#STESTN ;UPDATE TEST NUMBER
1431 005602 022737 000035 000404 CMP #35,@#STESTN ;SEQUENCE ERROR?
1432 005610 001012 BNE TST36-12 ;BR TO ERROR HALT ON SEQ ERROR
1433 005612 012706 000500 MOV #BUFF,SP ;STACK POINTER SETUP
1434 005616 012767 005626 172170 MOV #RETC4,RTRAP4 ;RETURN FROM TRAP POINTER
1435 005624 000003 TRT ;TRAP ON THIS INSTRUCTION
1436 005626 022767 005626 172640 RETC4: CMP #,BUFF-4 ;CHECK FOR INCREMENTED P.C.
1437 005634 001405 BEQ TST36
1438 005636 012737 000136 000402 MOV #136,@#SFATAL ;MOVE TO MAILBOX # ***** 136 *****
1439 005644 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
1440 005646 000000 HALT ;INCORRECT P.C. OR WRONG STESTN
1441 ; TO SCOPE REPLACE HALT W/ 240
1442 ; AND REPLACE NEXT INST W/ 760

```



# M03

```

1443
1444
1445
1446
1447 005650 005237 000404
1448 005654 022737 000036 000404
1449 005662 001044
1450 005664 012706 000500
1451 005670 012767 005712 172116
1452 005676 005067 005214
1453 005702 106467 005210
1454 005706 000257
1455 005710 000003
1456 005712 026727 172560 000000 RETD4:
1457 005720 001405
1458 005722 012737 000137 000402
1459 005730 005212
1460 005732 000000
1461
1462
1463 005734 012706 000500 1$: MOV #BUFF, SP
1464 005740 012767 005764 172046 MOV #RETE4, RTRAP4
1465 005746 012767 000357 005142 MOV #357, STATUS
1466 005754 106467 005136 MTPS STATUS
1467 005760 000277 SCC
1468 005762 000003 TRT
1469 005764 026727 172506 000357 RETE4: CMP BUFF-2, #357
1470 005772 001405 BEQ TST37
1471 005774 012737 000140 000402 MOV #140, #SFATAL
1472 006002 005212 INC (R2)
1473 006004 000000 HALT
1474
1475

;*****
;TEST 36 TEST THAT "OLD" STATUS AND PRIORITY ARE PLACED ON STACK
;*****
TST36: INC @#STESTN ;UPDATE TEST NUMBER
CMP #36, @#STESTN ;SEQUENCE ERROR?
BNE TST37-12 ;BR TO ERROR HALT ON SEQ ERROR
MOV #BUFF, SP ;SET UP
MOV #RETD4, RTRAP4 ;SET UP
CLR STATUS ;CLEAR STATUS AND PRIORITY
MTPS STATUS
CCC
TRT ;TRAP
CMP BUFF-2, #0 ;TEST THAT OLD STATUS WENT TO STACK
BEQ 1$
MOV #137, @#SFATAL ;MOVE TO MAILBOX # ***** 137 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;INCORRECT STATUS
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 753
1$: MOV #BUFF, SP ;SET UP
MOV #RETE4, RTRAP4 ;SET UP
MOV #357, STATUS ;SET PRIORITY
MTPS STATUS
SCC ;SET-SET CC
TRT ;TRAP
CMP BUFF-2, #357 ;COMPARES STATUS ON STACK
BEQ TST37
MOV #140, @#SFATAL ;MOVE TO MAILBOX # ***** 140 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;INCORRECT STATUS ON STACK, OR WRONG $TESTN
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 726
  
```

# N03

.MAIN. MACY11 27(1006) 17-FEB-77 15:39 PAGE 39  
 DVKADB.P11 17-FEB-77 15:34 T36

TEST THAT "OLD" STATUS AND PRIORITY ARE PLACED ON STACK

SEQ 0041

```

1476
1477
1478 ;*****
1479 ;TEST 37 TEST THAT "NEW" STATUS IS CORRECT
1480 ;*****
1480 006006 005237 000404 TST37: INC @#STESTN ;UPDATE TEST NUMBER
1481 006012 022737 000037 000404 CMP #37,@#STESTN ;SEQUENCE ERROR?
1482 006020 001125 BNE RSTP2 ;BR TO ERROR HALT ON SEQ ERROR
1483 006022 012706 000500 MOV #BUFF,SP
1484 006026 012767 006042 171760 MOV #RETF4,RTRAP4
1485 006034 005067 171756 CLR RTRAP4+2 ;CLEAR FUTURE PRIORITY AND CC
1486 006040 000003 TRT
1487 006042 RETF4:
1488 006042 100005 BPL 1$
1489 006044 012737 000141 000402 MOV #141,@#$FATAL ;MOVE TO MAILBOX # ***** 141 *****
1490 006052 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
1491 006054 000000 HALT ;C NOT CLEARED
1492 ; TO SCOPE REPLACE HALT W/ 240
1493 ; AND REPLACE NEXT INST W/ 761
1494 006056 1$:
1495 006056 001005 BNE 2$
1496 006060 012737 000142 000402 MOV #142,@#$FATAL ;MOVE TO MAILBOX # ***** 142 *****
1497 006066 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
1498 006070 000000 HALT ;Z NOT CLEARED
1499 ; TO SCOPE REPLACE HALT W/ 240
1500 ; AND REPLACE NEXT INST W/ 753
1501 006072 2$:
1502 006072 102005 BVC 3$
1503 006074 012737 000143 000402 MOV #143,@#$FATAL ;MOVE TO MAILBOX # ***** 143 *****
1504 006102 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
1505 006104 000000 HALT ;V NOT CLEARED
1506 ; TO SCOPE REPLACE HALT W/ 240
1507 ; AND REPLACE NEXT INST W/ 745
1508 006106 3$:
1509 006106 103005 BCC 4$
1510 006110 012737 000144 000402 MOV #144,@#$FATAL ;MOVE TO MAILBOX # ***** 144 *****
1511 006116 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
1512 006120 000000 HALT ;C NOT CLEARED
1513 ; TO SCOPE REPLACE HALT W/ 240
1514 ; AND REPLACE NEXT INST W/ 737
1515 006122 106767 004770 4$: MFPS STATUS
1516 006126 032767 000340 004762 BIT #340,STATUS ;TEST PRIORITY
1517 006134 001405 BEQ 5$
1518 006136 012737 000145 000402 MOV #145,@#$FATAL ;MOVE TO MAILBOX # ***** 145 *****
1519 006144 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
1520 006146 000000 HALT ;PRIORITY NOT ZERO
1521 ; TO SCOPE REPLACE HALT W/ 240
1522 ; AND REPLACE NEXT INST W/ 724
1523 006150 012706 000500 5$: MOV #BUFF,SP
1524 006154 012767 006172 171632 MOV #RETF4,RTRAP4
1525 006162 012767 000357 171626 MOV #357,RTRAP4+2 ;SET NEW "CC" AND PRIORITY
1526 006170 000003 TRT ;TRAP HERE
1527 006172 RETG4:
1528 006172 100405 BMI 1$
1529 006174 012737 000146 000402 MOV #146,@#$FATAL ;MOVE TO MAILBOX # ***** 146 *****
1530 006202 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
1531 006204 000000 HALT ;N NOT SET
  
```



# B04

MAIN. MACY11 27(1006) 17-FEB-77 15:39 PAGE 40  
 DVKADB.P11 17-FEB-77 15:34 T37

TEST THAT "NEW" STATUS IS CORRECT

SEG 0042

```

1532                                     ; TO SCOPE REPLACE HALT W/ 240
1533                                     ; AND REPLACE NEXT INST W/ 705
1534 006206                               1S:  BEQ      2S
1535 006206 001405                         MOV      #147, @#SFATAL
1536 006210 012737 000147 000402          INC      (R2)
1537 006216 005212                         HALT
1538 006220 000000
1539
1540                                     ; TO SCOPE REPLACE HALT W/ 240
1541 006222                               2S:  BVS      3S
1542 006222 102405                         MOV      #150, @#SFATAL
1543 006224 012737 000150 000402          INC      (R2)
1544 006232 005212                         HALT
1545 006234 000000
1546                                     ; TO SCOPE REPLACE HALT W/ 240
1547                                     ; AND REPLACE NEXT INST W/ 671
1548 006236                               3S:  BCS      4S
1549 006236 103405                         MOV      #151, @#SFATAL
1550 006240 012737 000151 000402          INC      (R2)
1551 006246 005212                         HALT
1552 006250 000000
1553                                     ; TO SCOPE REPLACE HALT W/ 240
1554                                     ; AND REPLACE NEXT INST W/ 663
1555 006252 106767 004640                   4S:  MFPS   STATUS
1556 006256 016706 004634                   MOV     STATUS, SP
1557 006262 042706 000017                   BIC    #17, SP
1558 006266 022706 000340                   CMP    #340, SP
1559 006272 001405                         BEQ    RST2
1560
1561 006274 012737 000152 000402  RSTP2:  MOV     #152, @#SFATAL
1562 006302 005212                         INC     (R2)
1563 006304 000000                         HALT
1564                                     ; MOVE TO MAILBOX # ***** 152 *****
1565                                     ; SET MSGTYP TO FATAL ERROR
1566 006306 012767 000016 171500  RST2:  MOV     #16, 14
1567 006314 005067 171476                         CLR     16
1568

```

```

1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579 006320 005237 000404
1580 006324 022737 000040 000404
1581 006332 001006
1582 006334 012706 000500
1583 006340 012767 006362 171436
1584 006346 000100
1585 006350 012737 000153 000402
1586 006356 005212
1587 006360 000000
1588
1589
1590 006362
1591
1592
1593
1594 006362 005237 000404
1595 006366 022737 000041 000404
1596 006374 001011
1597 006376 012706 000500
1598 006402 012767 006412 171374
1599 006410 000100
1600 006412 020627 000474
1601 006416 001405
1602 006420 012737 000154 000402
1603 006426 005212
1604 006430 000000
1605
1606

```

```

;PDP-11 ILLEGAL AND ADDRESS INSTRUCTION TEST
;ALL INSTRUCTIONS THAT ARE RESERVED
;SHOULD TRAP TO LOCATION 4, AND THE
;PC THAT POINTS TO THE TRAPPING INSTRUCTION
;SHOULD BE PLACED ON THE STACK

```

```

;*****
;TEST 40 TEST THAT A TRAP OCCURS ON AN ILLEGAL INSTRUCTION
;*****
TST40: INC @#STESTN ;UPDATE TEST NUMBER
        CMP #40,@#STESTN ;SEQUENCE ERROR?
        BNE TST41-12 ;BR TO ERROR HALT ON SEQ ERROR
        MOV #BUFF,SP ;STACK POINTER SETUP
        MOV #RETAS,RTRAPS ;RETURN LOCATION
        JMP %0 ;ILLEGAL INSTRUCTION, SHOULD TRAP
        MOV #153,@#SFATAL ;MOVE TO MAILBOX # ***** 153 *****
        INC (R2) ;SET MSGTYP TO FATAL ERROR
        HALT ;DID NOT TRAP, OR WRONG $TESTN
        ; TO SCOPE REPLACE HALT W/ 240
        ; AND REPLACE NEXT INST W/ 764

```

```

RETAS:
;*****
;TEST 41 TEST DECREMENT OF STACK POINTER ON A TRAP OPERATION
;*****
TST41: INC @#STESTN ;UPDATE TEST NUMBER
        CMP #41,@#STESTN ;SEQUENCE ERROR?
        BNE TST42-12 ;BR TO ERROR HALT ON SEQ ERROR
        MOV #BUFF,SP ;STACK POINTER SETUP
        MOV #RETB5,RTRAPS ;RETURN POINTER
        JMP %0 ;RESERVED INSTRUCTION
RETBS: CMP SP,#BUFF-4 ;TEST DECREMENT OF SP
        BEQ TST42
        MOV #154,@#SFATAL ;MOVE TO MAILBOX # ***** 154 *****
        INC (R2) ;SET MSGTYP TO FATAL ERROR
        HALT ;NOT DECREMENTED TWO WORDS, OR WRONG $TESTN
        ; TO SCOPE REPLACE HALT W/ 240
        ; AND REPLACE NEXT INST W/ 761

```



```

1607
1608
1609
1610
1611 006432 005237 000404
1612 006436 022737 000042 000404
1613 006444 001012
1614 006446 012706 000500
1615 006452 012767 006462 171324
1616 006460 000100
1617 006462 022767 006462 172004 RETC5:
1618 006470 001405
1619 006472 012737 000155 000402
1620 006500 005212
1621 006502 000000
1622
1623
1624
1625
1626
1627 006504 005237 000404
1628 006510 022737 000043 000404
1629 006516 001044
1630 006520 012706 000500
1631 006524 012767 006546 171252
1632 006532 005067 004360
1633 006536 106467 004354
1634 006542 000257
1635 006544 000100
1636 006546 026727 171724 000000 RETD5:
1637 006554 001405
1638 006556 012737 000156 000402
1639 006564 005212
1640 006566 000000
1641
1642
1643 006570 012706 000500 1$:
1644 006574 012767 006620 171202
1645 006602 012767 000357 004306
1646 006610 106467 004302
1647 006614 000277
1648 006616 000100
1649 006620 026727 171652 000357 RETE5:
1650 006626 001405
1651 006630 012737 000157 000402
1652 006636 005212
1653 006640 000000
1654
1655

```

```

;*****
;TEST 42 TEST THAT PROPER P.C. IS SAVED
;*****
TST42: INC @#STESTN ;UPDATE TEST NUMBER
        CMP #42,@#STESTN ;SEQUENCE ERROR?
        BNE TST43-12 ;BR TO ERROR HALT ON SEQ ERROR
        MOV #BUFF,SP ;STACK POINTER SETUP
        MOV #RETC5,RTRAPS ;RETURN FROM TRAP POINTER
        JMP %0 ;TRAP ON THIS INSTRUCTION
RETC5:  CMP #. ,BUFF-4 ;CHECK FOR INCREMENTED P.C.
        BEQ TST43
        MOV #155,@#SFATAL ;MOVE TO MAILBOX # ***** 155 *****
        INC (R2) ;SET MSGTYP TO FATAL ERROR
        HALT ;INCORRECT P.C. OR WRONG $TESTN
        ; TO SCOPE REPLACE HALT W/ 240
        ; AND REPLACE NEXT INST W/ 760
;*****
;TEST 43 TEST THAT "OLD" STATUS AND PRIORITY ARE PLACED ON STACK
;*****
TST43:  INC @#STESTN ;UPDATE TEST NUMBER
        CMP #43,@#STESTN ;SEQUENCE ERROR?
        BNE TST44-12 ;BR TO ERROR HALT ON SEQ ERROR
        MOV #BUFF,SP ;SET UP
        MOV #RETD5,RTRAPS ;SET UP
        CLR STATUS ;CLEAR STATUS AND PRIORITY
        MTPS STATUS
        JMP %0 ;TRAP
RETD5:  CMP BUFF-2,#0 ;TEST THAT OLD STATUS WENT TO STACK
        BEQ 1$
        MOV #156,@#SFATAL ;MOVE TO MAILBOX # ***** 156 *****
        INC (R2) ;SET MSGTYP TO FATAL ERROR
        HALT ;INCORRECT STATUS
        ; TO SCOPE REPLACE HALT W/ 240
        ; AND REPLACE NEXT INST W/ 753
1$:     MOV #BUFF,SP ;SET UP
        MOV #RETE5,RTRAPS ;SET UP
        MOV #357,STATUS ;SET PRIORITY
        MTPS STATUS
        SCC ;SET CC
        JMP %0 ;TRAP
RETE5:  CMP BUFF-2,#357 ;COMPARES STATUS ON STACK
        BEQ TST44
        MOV #157,@#SFATAL ;MOVE TO MAILBOX # ***** 157 *****
        INC (R2) ;SET MSGTYP TO FATAL ERROR
        HALT ;INCORRECT STATUS ON STACK, OR WRONG $TESTN
        ; TO SCOPE REPLACE HALT W/ 240
        ; AND REPLACE NEXT INST W/ 726

```

# E04

```

1656
1657
1658
1659
1660 006642 005237 000404
1661 006646 022737 000044 000404
1662 006654 001123
1663 006656 012706 000500
1664 006662 012767 006676 171114
1665 006670 005067 171112
1666 006674 000100
1667 006676
1668 006676 100005
1669 006700 012737 000160 000402
1670 006706 005212
1671 006710 000000
1672
1673
1674 006712
1675 006712 001005
1676 006714 012737 000161 000402
1677 006722 005212
1678 006724 000000
1679
1680
1681 006726
1682 006726 102005
1683 006730 012737 000162 000402
1684 006736 005212
1685 006740 000000
1686
1687
1688 006742
1689 006742 103005
1690 006744 012737 000163 000402
1691 006752 005212
1692 006754 000000
1693
1694
1695 006756 106767 004134
1696 006762 032767 000357 004126
1697 006770 001405
1698 006772 012737 000164 000402
1699 007000 005212
1700 007002 000000
1701
1702
1703 007004 012706 000500
1704 007010 012767 007026 170766
1705 007016 012767 000357 170762
1706 007024 000100
1707 007026
1708 007026 100405
1709 007030 012737 000165 000402
1710 007036 005212
1711 007040 000000

```

```

;*****
;TEST 44 TEST THAT "NEW" STATUS IS CORRECT
;*****
TST44: INC @#STESTN ;UPDATE TEST NUMBER
CMP #44,@#STESTN ;SEQUENCE ERROR?
BNE TST45-12 ;BR TO ERROR HALT ON SEQ ERROR
MOV #BUFF,SP
MOV #RETF5,RTRAPS
CLR RTRAPS+2 ;CLEAR FUTURE PRIORITY AND CC
JMP %0

RETF5: BPL 1$
MOV #160,@#SFATAL ;MOVE TO MAILBOX # ***** 160 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;C NOT CLEARED
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 761

1$: BNE 2$
MOV #161,@#SFATAL ;MOVE TO MAILBOX # ***** 161 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;Z NOT CLEARED
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 753

2$: BVC 3$
MOV #162,@#SFATAL ;MOVE TO MAILBOX # ***** 162 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;V NOT CLEARED
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 745

3$: BCC 4$
MOV #163,@#SFATAL ;MOVE TO MAILBOX # ***** 163 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;C NOT CLEARED
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 737

4$: MFPS STATUS
BIT #357,STATUS ;TEST PRIORITY
BEQ 5$
MOV #164,@#SFATAL ;MOVE TO MAILBOX # ***** 164 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;PRIORITY NOT ZERO
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 724

5$: MOV #BUFF,SP
MOV #RETF5,RTRAPS
MOV #357,RTRAPS+2 ;SET NEW "CC" AND PRIORITY
JMP %0 ;TRAP HERE

RETF5: BMI 1$
MOV #165,@#SFATAL ;MOVE TO MAILBOX # ***** 165 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;N NOT SET

```









```

1776
1777
1778
1779
1780 007250 005237 000404
1781 007254 022737 000047 000404
1782 007262 001012
1783 007264 012706 000500
1784 007270 012767 007300 170506
1785 007276 004000
1786 007300 022767 007300 171166
1787 007306 001405
1788 007310 012737 000174 000402
1789 007316 005212
1790 007320 000000
1791
1792
1793
1794
1795
1796
1797 007322 005237 000404
1798 007326 022737 000050 000404
1799 007334 001044
1800 007336 012706 000500
1801 007342 012767 007364 170434
1802 007350 005067 003542
1803 007354 106467 003536
1804 007360 000257
1805 007362 004000
1806 007364 026727 171106 000000
1807 007372 001405
1808 007374 012737 000175 000402
1809 007402 005212
1810 007404 000000
1811
1812
1813 007406 012706 000500
1814 007412 012767 007436 170364
1815 007420 012767 000357 003470
1816 007426 106467 003464
1817 007432 000277
1818 007434 004000
1819 007436 026727 171034 000357
1820 007444 001405
1821 007446 012737 000176 000402
1822 007454 005212
1823 007456 000000
1824
1825
1826
1827
1828
1829
1830 007460 005237 000404
1831 007464 022737 000051 000404

;*****
;TEST 47 TEST THAT PROPER P.C. IS SAVED
;*****
TST47: INC @#STESTN ;UPDATE TEST NUMBER
        CMP #47,@#STESTN ;SEQUENCE ERROR?
        BNE TST50-12 ;BR TO ERROR HALT ON SEQ ERROR
        MOV #BUFF,SP ;STACK POINTER SETUP
        MOV #RETK,RTRAPS ;RETURN FROM TRAP POINTER
INSTK: JSR %0,%0 ;TRAP ON THIS INSTRUCTION
RETK: CMP #INSTK+2,BUFF-4 ;CHECK FOR INCREMENTED P.C.
        BEQ TST50
        MOV #174,@#SFATAL ;MOVE TO MAILBOX # ***** 174 *****
        INC (R2) ;SET MSGTYP TO FATAL ERROR
        HALT ;INCORRECT P.C. OR WRONG $TESTN
        ; TO SCOPE REPLACE HALT W/ 240
        ; AND REPLACE NEXT INST W/ 760

;*****
;TEST 50 TEST THAT "OLD" STATUS AND PRIORITY ARE PLACED ON STACK
;*****
TST50: INC @#STESTN ;UPDATE TEST NUMBER
        CMP #50,@#STESTN ;SEQUENCE ERROR?
        BNE TST51-12 ;BR TO ERROR HALT ON SEQ ERROR
        MOV #BUFF,SP ;SET UP
        MOV #RETL,RTRAPS ;SET UP
        CLR STATUS ;CLEAR STATUS AND PRIORITY
        MTPS STATUS
        JSR %0,%0 ;TRAP
RETL: CMP BUFF-2,#0 ;TEST THAT OLD STATUS WENT TO STACK
        BEQ 1$
        MOV #175,@#SFATAL ;MOVE TO MAILBOX # ***** 175 *****
        INC (R2) ;SET MSGTYP TO FATAL ERROR
        HALT ;INCORRECT STATUS
        ; TO SCOPE REPLACE HALT W/ 240
        ; AND REPLACE NEXT INST W/ 753

1$: MOV #BUFF,SP ;SET UP
   MOV #RETM,RTRAPS ;SET UP
   MOV #357,STATUS ;SET PRIORITY
   MTPS STATUS
   SCC ;SET CC
   JSR %0,%0 ;TRAP
RETM: CMP BUFF-2,#357 ;COMPARES STATUS ON STACK
        BEQ TST51
        MOV #176,@#SFATAL ;MOVE TO MAILBOX # ***** 176 *****
        INC (R2) ;SET MSGTYP TO FATAL ERROR
        HALT ;INCORRECT STATUS ON STACK, OR WRONG $TESTN
        ; TO SCOPE REPLACE HALT W/ 240
        ; AND REPLACE NEXT INST W/ 726

;*****
;TEST 51 TEST THAT "NEW" STATUS IS CORRECT
;*****
TST51: INC @#STESTN ;UPDATE TEST NUMBER
        CMP #51,@#STESTN ;SEQUENCE ERROR?

```

THAT "NEW" STATUS IS CORRECT

SEG 0049

1832	007472	001122			BNE	STP1		;BR TO ERROR HALT ON SEQ ERRCR
1833	007474	012706	000500		MOV	#BUFF,SP		
1834	007500	012767	007514	170276	MOV	#RETN,RTRAPS		
1835	007506	005067	170274		CLR	RTRAPS+2		;CLEAR FUTURE PRIORITY AND CC
1836	007512	004000			JSR	%0,%0		
1837	007514						RETN:	;TEST FOR "C" CLEARED
1838	007514	100005			BPL	1\$		
1839	007516	012737	000177	000402	MOV	#177,@#\$FATAL		;MOVE TO MAILBOX # ***** 177 *****
1840	007524	005212			INC	(R2)		;SET MSGTYP TO FATAL ERROR
1841	007526	000000			HALT			;C NOT CLEARED
1842								; TO SCOPE REPLACE HALT W/ 240
1843								; AND REPLACE NEXT INST W/ 761
1844	007530						1\$:	
1845	007530	001005			BNE	2\$		
1846	007532	012737	000200	000402	MOV	#200,@#\$FATAL		;MOVE TO MAILBOX # ***** 200 *****
1847	007540	005212			INC	(R2)		;SET MSGTYP TO FATAL ERROR
1848	007542	000000			HALT			;Z NOT CLEARED
1849								; TO SCOPE REPLACE HALT W/ 240
1850								; AND REPLACE NEXT INST W/ 753
1851	007544						2\$:	
1852	007544	102005			BVC	3\$		
1853	007546	012737	000201	000402	MOV	#201,@#\$FATAL		;MOVE TO MAILBOX # ***** 201 *****
1854	007554	005212			INC	(R2)		;SET MSGTYP TO FATAL ERROR
1855	007556	000000			HALT			;V NOT CLEARED
1856								; TO SCOPE REPLACE HALT W/ 240
1857								; AND REPLACE NEXT INST W/ 745
1858	007560						3\$:	
1859	007560	103005			BCC	4\$		
1860	007562	012737	000202	000402	MOV	#202,@#\$FATAL		;MOVE TO MAILBOX # ***** 202 *****
1861	007570	005212			INC	(R2)		;SET MSGTYP TO FATAL ERROR
1862	007572	000000			HALT			;C NOT CLEARED
1863								; TO SCOPE REPLACE HALT W/ 240
1864								; AND REPLACE NEXT INST W/ 737
1865	007574	106767	003316		MFPS	STATUS		
1866	007600	016700	003312		MOV	STATUS,%0		;TEMP STORAGE
1867	007604	001405			BEQ	5\$		
1868	007606	012737	000203	000402	MOV	#203,@#\$FATAL		;MOVE TO MAILBOX # ***** 203 *****
1869	007614	005212			INC	(R2)		;SET MSGTYP TO FATAL ERROR
1870	007616	000000			HALT			;PRIORITY NOT ZERO
1871								; TO SCOPE REPLACE HALT W/ 240
1872								; AND REPLACE NEXT INST W/ 725
1873	007620	012706	000500		MOV	#BUFF,SP		
1874	007624	012767	007642	170152	MOV	#RETO,RTRAPS		
1875	007632	012767	000357	170146	MOV	#357,RTRAPS+2		;SET NEW "CC" AND PRIORITY
1876	007640	004000			JSR	%0,%0		;TRAP HERE
1877	007642						RETO:	
1878	007642	100405			BMI	1\$		
1879	007644	012737	000204	000402	MOV	#204,@#\$FATAL		;MOVE TO MAILBOX # ***** 204 *****
1880	007652	005212			INC	(R2)		;SET MSGTYP TO FATAL ERROR
1881	007654	000000			HALT			;N NOT SET
1882								; TO SCOPE REPLACE HALT W/ 240
1883								; AND REPLACE NEXT INST W/ 706
1884	007656						1\$:	
1885	007656	001405			BEQ	2\$		
1886	007660	012737	000205	000402	MOV	#205,@#\$FATAL		;MOVE TO MAILBOX # ***** 205 *****
1887	007666	005212			INC	(R2)		;SET MSGTYP TO FATAL ERROR



J04

MAIN, MACY11 27(1006) 17-FEB-77 15:39 PAGE 48  
DVKADB.P11 17-FEB-77 15:34 TSI TEST

THAT "NEW" STATUS IS CORRECT

SEG 0050

```

1888 007670 000000          HALT          ;Z NOT SET
1889                                     ; TO SCOPE REPLACE HALT W/ 24C
1890                                     ; AND REPLACE NEXT INST W/ 700
1891 007672          2$:      BVS          3$
1892 007672 102405          MOV          #206,2#$FATAL ;MOVE TO MAILBOX # ***** 206 *****
1893 007674 012737 000206 000402  INC          (R2)      ;SET MSGTYP TO FATAL ERROR
1894 007702 005212          HALT          ;V NOT SET
1895 007704 000000          ; TO SCOPE REPLACE HALT W/ 240
1896                                     ; AND REPLACE NEXT INST W/ 672
1897
1898 007706          3$:      BCS          4$
1899 007706 103405          MOV          #207,2#$FATAL ;MOVE TO MAILBOX # ***** 207 *****
1900 007710 012737 000207 000402  INC          (R2)      ;SET MSGTYP TO FATAL ERROR
1901 007716 005212          HALT          ;C NOT SET
1902 007720 000000          ; TO SCOPE REPLACE HALT W/ 240
1903                                     ; AND REPLACE NEXT INST W/ 664
1904
1905 007722 106767 003170 4$:      MFPS      STATUS
1906 007726 016700 003164      MOV          STATUS,%0
1907 007732 022700 000357      CMP          #357,%0
1908 007736 001405          BEQ          STPBB
1909 007740          STP1:
1910 007740 012737 000210 000402  MOV          #210,2#$FATAL ;MOVE TO MAILBOX # ***** 210 *****
1911 007746 005212          INC          (R2)      ;SET MSGTYP TO FATAL ERROR
1912 007750 000000          HALT          ;PRIORITY WAS CHANGED, OR WRONG $TESTN
1913                                     ; TO SCOPE REPLACE HALT W/ 240
1914                                     ; AND REPLACE NEXT INST W/ 650
1915 007752 012767 000006 170024  STPBB:  MOV          #6,4
1916 007760 005067 170022      CLR          6

```

K04

```

1917
1918
1919
1920
1921 007764 005237 000404
1922 007770 022737 000052 000404
1923 007776 001013
1924 010000 012706 000500
1925 010004 012767 010040 170002
1926 010012 012746 000020
1927 010016 012746 010024
1928 010022 000002
1929 010024 000240
1930 010026 012737 000211 000402
1931 010034 005212
1932 010036 000000
1933
1934
1935 010040
1936
1937
1938
1939 010040 005237 000404
1940 010044 022737 000053 000404
1941 010052 001023
1942 010054 012706 000500
1943 010060 012767 010114 167726
1944 010066 012746 000020
1945 010072 012746 010100
1946 010076 000002
1947 010100 000240
1948 010102 012737 000212 000402
1949 010110 005212
1950 010112 000000
1951
1952
1953 010114 020627 000474
1954 010120 001405
1955 010122 012737 000213 000402
1956 010130 005212
1957 010132 000000
1958
1959
;*****
;TEST 52 TEST THAT THE TRACE TRAP; (BIT4 20(8)) WILL CAUSE A TRAP TO 14
;*****
TST52: INC @#STESTN ;UPDATE TEST NUMBER
        CMP #52,@#STESTN ;SEQUENCE ERROR?
        BNE TST53-12 ;BR TO ERROR HALT ON SEQ ERROR
        MOV #BUFF,SP
        MOV #RETAT,RTRAP4 ;SET UP TO TRAP TO 14
        MOV #20,-(SP) ;PUSH T BIT
        MOV #.+6,-(SP) ;PUSH PC
        RTI ;SET T BIT
        NOP ;TRAP HERE
        MOV #211,@#$FATAL ;MOVE TO MAILBOX # ***** 211 *****
        INC (R2) ;SET MSGTYP TO FATAL ERROR
        HALT ;TRACE BIT DID NOT TRAP!,OR WRONG $TESTN
        ; TO SCOPE REPLACE HALT W/ 240
        ; AND REPLACE NEXT INST W/ 757

RETAT:
;*****
;TEST 53 TEST STACK POINTER DECREMENTS
;*****
TST53: INC @#STESTN ;UPDATE TEST NUMBER
        CMP #53,@#STESTN ;SEQUENCE ERROR?
        BNE TST54-12 ;BR TO ERROR HALT ON SEQ ERROR
        MOV #BUFF,SP
        MOV #RETBT,RTRAP4 ;PUSH T BIT
        MOV #20,-(SP) ;PUSH PC
        MOV #.+6,-(SP) ;SET T BIT
        RTI ;TRAP HERE
        NOP ;TRAP HERE
        MOV #212,@#$FATAL ;MOVE TO MAILBOX # ***** 212 *****
        INC (R2) ;SET MSGTYP TO FATAL ERROR
        HALT ;TRACE BIT DID NOT TRAP!
        ; TO SCOPE REPLACE HALT W/ 240
        ; AND REPLACE NEXT INST W/ 757

RETBT: CMP SP,#BUFF-4
        BEQ TST54
        MOV #213,@#$FATAL ;MOVE TO MAILBOX # ***** 213 *****
        INC (R2) ;SET MSGTYP TO FATAL ERROR
        HALT ;STACK POINTER WAS NOT PUSHED BY TRAP,OR WRONG $TESTN
        ; TO SCOPE REPLACE HALT W/ 240
        ; AND REPLACE NEXT INST W/ 747
    
```



```

1960
1961
1962
1963
1964 010134 005237 000404
1965 010140 022737 000054 000404
1966 010146 001016
1967 010150 012706 000500
1968 010154 012767 010174 167632
1969 010162 012746 000020
1970 010166 012746 010174
1971 010172 000002
1972
1973 010174 022767 010174 170272 RETCT: CMP #. BUFF-4
1974 010202 001405 BEQ TST55
1975 010204 012737 000214 000402 MOV #214, @#$FATAL ;MOVE TO MAILBOX # ***** 214 *****
1976 010212 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
1977 010214 000000 HALT ;CORRECT PC WAS NOT SAVED ON STACK, OR WRONG $TESTN
1978 ; TO SCOPE REPLACE HALT W/ 240
1979 ; AND REPLACE NEXT INST W/ 754
1980
1981
1982
1983
1984
1985 010216 005237 000404
1986 010222 022737 000055 000404
1987 010230 001015
1988
1989 010232 012706 000500
1990 010236 005001
1991 010240 012746 000020
1992 010244 012746 010260
1993 010250 012767 010276 167536
1994 010256 000006
1995 010260 000240
1996 010262 001405
1997 010264 012737 000215 000402
1998 010272 005212
1999 010274 000000
2000
2001
2002
2003 010276

;*****
;TEST 54 TEST FOR PROPER PC ON STACK
;*****
TST54: INC @#$TESTN ;UPDATE TEST NUMBER
CMP #54, @#$TESTN ;SEQUENCE ERROR?
BNE TST55-12 ;BR TO ERROR HALT ON SEQ ERROR
MOV #BUFF, SP
MOV #RETCT, RTRAP4
MOV #20, -(SP) ;PUSH T BIT
MOV #.+6, -(SP) ;PUSH PC
RTI ;SET T BIT
;TRAP HERE

RETCT: CMP #. BUFF-4
BEQ TST55
MOV #214, @#$FATAL ;MOVE TO MAILBOX # ***** 214 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;CORRECT PC WAS NOT SAVED ON STACK, OR WRONG $TESTN
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 754

;*****
;TEST 55 TEST THAT RTT POPS T- BIT
;*****
TST55: INC @#$TESTN ;UPDATE TEST NUMBER
CMP #55, @#$TESTN ;SEQUENCE ERROR?
BNE TST56-12 ;BR TO ERROR HALT ON SEQ ERROR
MOV #BUFF, SP
CLR R1 ;CLEAR R1
MOV #20, -(SP)
MOV #RTT1, -(SP)
MOV #RTT2, 14
RTT: NOP
BEQ TST56
MOV #215, @#$FATAL ;MOVE TO MAILBOX # ***** 215 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;T-BIT DID NOT TRAP, OR WRONG $TESTN
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 755

RTT2:
    
```

M04

```

2004
2005
2006
2007
2008 010276 005237 000404
2009 010302 022737 000056 000404
2010 010310 001031
2011 010312 012705 177777
2012 010316 012706 000500
2013 010322 012746 000020
2014 010326 012746 010344
2015 010332 012767 010364 167454
2016 010340 005001
2017 010342 000006
2018 010344 005201
2019 010346 005205
2020 010350 001762
2021 010352 012737 000216 000402
2022 010360 005212
2023 010362 000000
2024
2025
2026 010364 005301
2027 010366 001407
2028 010370 005205
2029 010372 001751
2030 010374 012737 000217 000402
2031 010402 005212
2032 010404 000000
2033
2034
2035 010406

```

```

:*****
:TEST 56 TEST THAT RTT ALLOWS ONE INST. BEFORE TRAP
:*****
TST56: INC @#STESTN ;UPDATE TEST NUMBER
CMP #56,@#STESTN ;SEQUENCE ERROR?
BNE TST57-12 ;BR TO ERROR HALT ON SEQ ERROR
MOV #177777,%5
RTT5: MOV #BUFF,SP
MOV #20,-(SP)
MOV #RTT3,-(SP)
MOV #RTT4,14
CLR R1 ;CLEAR R0
RTT ;SET T-BIT
RTT3: INC R1
INC %5
BEQ RTT5 ;DO THIS TEST NO MORE THAN 2 TIMES
MOV #216,@#SFATAL ;MOVE TO MAILBOX # ***** 216 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;DID NOT TRAP
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 752
;SEE IF RTT ALLOWS 1 INST.
RTT4: DEC R1
BEQ RTT6
INC %5 ;DO THIS TEST NO MORE THAN TWO TIMES
BEQ RTT5
MOV #217,@#SFATAL ;MOVE TO MAILBOX # ***** 217 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;RTT DID NOT ALLOW 1 INST.,OR WRONG $TESTN
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 741
RTT6:

```



```

2036
2037
2038 ;*****
;TEST 57 TEST THAT RTI DOES NOT ALLOW 1 INST.
2039 ;*****
2040 010406 005237 000404 TST57: INC @#STESTN ;UPDATE TEST NUMBER
2041 010412 022737 000057 000404 CMP #57,@#STESTN ;SEQUENCE ERROR?
2042 010420 001023 BNE TST60-12 ;BR TO ERROR HALT ON SEQ ERROR
2043 010422 012706 000500 MOV #BUFF,SP
2044 010426 012746 000020 MOV #20,-(SP)
2045 010432 012746 010450 MOV #RTI1,-(SP)
2046 010436 012767 010464 167350 MOV #RTI2,14
2047 010444 005001 CLR R1
2048 010446 000002 RTI ;SET T-BIT
2049 010450 005201 RTI1: INC R1 ;RTI SHOULD NOT ALLOW THIS
2050 010452 012737 000220 000402 MOV #220,@#SFATAL ;MOVE TO MAILBOX # ***** 220 *****
2051 010460 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
2052 010462 000000 HALT ;T- BIT DID NOT CAUSE TRAP
2053 ; TO SCOPE REPLACE HALT W/ 240
2054 ; AND REPLACE NEXT INST W/ 756
2055 010464 005701 RTI2: TST R1 ;RTI SHOULD NOT ALLOW 1 INST. BEFORE TRAP
2056
2057 010466 001405 BEQ TST60
2058 010470 012737 000221 000402 MOV #221,@#SFATAL ;MOVE TO MAILBOX # ***** 221 *****
2059 010476 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
2060 010500 000000 HALT ;RTI DID ALLOW 1 INST. BEFORE TRAP,OR WRONG $TESTN
2061 ; TO SCOPE REPLACE HALT W/ 240
2062 ; AND REPLACE NEXT INST W/ 747

```

```

2063
2064
2065      ;*****
2066      ;TEST 60      TEST TRAP ON TRAP
2067      ;*****
2067 010502 005237 000404      †ST60: INC      @#STESTN      ;UPDATE TEST NUMBER
2068 010506 022737 000060 000404      CMP      #60,@#STESTN      ;SEQUENCE ERROR?
2069 010514 001033      BNE      TRACE      ;BR TO ERROR HALT ON SEQ ERROR
2070      ;TEST THAT TRACE BIT TRAPS ARE INHIBITED ON TRAP INST
2071
2072 010516 012705 177777      TRPTRP: MOV      #177777,%5
2073 010522 012706 000500      MOV      #BUFF,%6
2074 010526 012767 010600 167260      MOV      #TRACE1,14      ;TRACE TRAP
2075 010534 005027 000016      CLR      #16      ;
2076 010540 005027 000022      CLR      #22      ;
2077 010544 012767 010616 167246      MOV      #TONT1,20      ;IOT TRAP
2078 010552 012746 000020      MOV      #20,-(SP)      ;PUSH T BIT
2079 010556 012746 010564      MOV      #.+6,-(SP)      ;PUSH PC
2080 010562 000006      RTT      ;SET T BIT
2081 010564 000004      IOT      ;TRAP, NEW STATUS HAVE TRACE RESET
2082 010566 012737 000222 000402      MOV      #222,@#SFATAL      ;MOVE TO MAILBOX # ***** 222 *****
2083 010574 005212      INC      (R2)      ;SET MSGTYP TO FATAL ERROR
2084 010576 000000      HALT      ;NO TRAP OCCURRED
2085      ; TO SCOPE REPLACE HALT W/ 240
2086      ; AND REPLACE NEXT INST W/ 746
2087 010600 005205      TRACE1: INC      %5      ;IF FAILED TRY THIS TEST TWICE BUT NO MORE
2088 010602 001747      BEQ      TRPTRP
2089 010604      TRACE:
2090 010604 012737 000223 000402      MOV      #223,@#SFATAL      ;MOVE TO MAILBOX # ***** 223 *****
2091 010612 005212      INC      (R2)      ;SET MSGTYP TO FATAL ERROR
2092 010614 000000      HALT      ;IOT SHOULD HAVE CLEARED THE T BIT,OR WRONG $TESTN
2093      ; TO SCOPE REPLACE HALT W/ 240
2094      ; AND REPLACE NEXT INST W/ 737
2095 010616 012767 000016 167170      TONT1: MOV      #16,14
2096 010624 012767 000022 167166      MOV      #22,20
    
```



```

2097
2098
2099
2100
2101 010632 005237 000404
2102 010636 022737 000061 000404
2103 010644 001026
2104 010646 012706 000500
2105 010652 012767 010712 167134
2106 010660 005067 167132
2107 010664 012746 000020
2108 010670 012746 010676
2109 010674 000002
2110 010676 000240
2111 010700 012737 000224 000402
2112 010706 005212
2113 010710 000000
2114
2115
2116 010712 036727 167560 000020 TRC1: BIT BUFF-2, #20
2117 010720 001005 BNE TST62
2118 010722 012737 000225 000402 MOV #225, @#$FATAL
2119 010730 005212 INC (R2)
2120 010732 000000 HALT
2121
2122
2123
2124
2125
2126 010734 005237 000404
2127 010740 022737 000062 000404
2128 010746 001020
2129 010750 012706 000500
2130 010754 012746 000020
2131 010760 012746 010774
2132 010764 012767 011010 167022
2133 010772 000002
2134
2135 010774 000240 TRC2: NOP
2136 010776 012737 000226 000402 MOV #226, @#$FATAL
2137 011004 005212 INC (R2)
2138 011006 000000 HALT
2139
2140
2141
2142 011010 012767 000016 166776 TRC3: MOV #16, 14
2143 011016 005067 166774 CLR 16

```

```

:*****
;TEST 61 TEST THAT THE TRACE BIT WILL CAUSE A TRAP
:*****
TST61: INC @#$TESTN ;UPDATE TEST NUMBER
CMP #61, @#$TESTN ;SEQUENCE ERROR?
BNE TST62-12 ;BR TO ERROR HALT ON SEQ ERROR
MOV #BUFF, %6 ;SET UP STACK POINTER
MOV #TRC1, 14 ;TRACE TRAP RETURN
CLR 16
MOV #20, -(SP) ;PUSH T BIT
MOV #.+6, -(SP) ;PUSH PC
RTI ;SET T BIT
NOP
MOV #224, @#$FATAL ;MOVE TO MAILBOX # ***** 224 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;DO NOT TRAP
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 755
;CHECK FOR T BIT ON STACK
TRC1: BIT BUFF-2, #20
BNE TST62
MOV #225, @#$FATAL ;MOVE TO MAILBOX # ***** 225 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;T BIT NOT SAVED ON STACKED, OR WRONG $TESTN
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 744
:*****
;TEST 62 TEST THAT AN RTI POPS THE T BIT
:*****
TST62: INC @#$TESTN ;UPDATE TEST NUMBER
CMP #62, @#$TESTN ;SEQUENCE ERROR?
BNE TST63-12 ;BR TO ERROR HALT ON SEQ ERROR
MOV #BUFF, %6 ;SET UP THE STACK
MOV #20, -(6) ;FUTURE T BIT ON STACK
MOV #TRC2, -(6) ;RTI RETURN
MOV #TRC3, 14 ;TRACE TRAP INTERRUPT POINTER
RTI
NOP
MOV #226, @#$FATAL ;TRACE IS SET SHOULD TRAP TO 14
INC (R2) ;MOVE TO MAILBOX # ***** 226 *****
HALT ;SET MSGTYP TO FATAL ERROR
;DID NOT TRACE TRAP, OR WRONG $TESTN
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 757

```

```

2144
2145 ;*****
2146 ;TEST 63 TEST THAT A PENDING INTERRUPT OCCURS BEFORE TRAP
2147 ;*****
2148 011022 005237 000404 TST63: INC @#STESTN ;UPDATE TEST NUMBER
2149 011026 022737 000063 000404 CMP #63,@#STESTN ;SEQUENCE ERROR?
2150 011034 001052 BNE TR1 ;BR TO ERROR HALT ON SEQ ERROR
2151 011036 032767 000001 167354 BIT #1,$ENV ;CHECK IF ON APT
2152 011044 001403 BEQ NOAPT ;IF NOT ON APT
2153 011046 005767 167334 TST $PASS ;CHECK IF ON FIRST PASS
2154 011052 001052 BNE TST64 ;IF NOT FIRST PASS
2155 011054 NOAPT:
2156 011054 105737 177564 TSTB @#TPS
2157 011060 100375 BPL .-4
2158 011062 012706 000500 MOV #BUFF,%6
2159 011066 012767 000340 002022 MOV #340,$STATUS ;HIGHEST PRIORITY LEVEL
2160 011074 106467 002016 MTPS STATUS
2161 011100 012767 011150 166756 MOV #TR0,64
2162 011106 012767 000100 166450 MOV #100,TTCSR ;INTERRUPT FOR TTY PUNCH/PRINTER
2163 011114 012767 011162 166712 MOV #TR1,34 ;TRAP VECTOR
2164 011122 012767 011174 166734 MOV #TR2,64 ;TTY VECTOR
2165 011130 012767 000340 166700 MOV #340,36 ;IF TRAP TRAPS, MOVE 340 TO PRIORITY
2166 011136 005067 001754 CLR STATUS ;SHOULD TRAP AT END OF CLR INST
2167 011142 106467 001750 MTPS STATUS
2168 011146 104400 TRAP ;TTY INTERRUPT SHOULD OVERRIDE TRAP
2169 011150
2170 011150 012737 000227 000402 TR0: MOV #227,@#SFATAL ;MOVE TO MAILBOX # ***** 227 *****
2171 011156 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
2172 011160 000000 HALT ;TTY SHOULDN'T HAVE INTERRUPTED
2173 ; TO SCOPE REPLACE HALT W/ 240
2174 ; AND REPLACE NEXT INST W/ 725
2175 011162
2176 011162 012737 000230 000402 TR1: MOV #230,@#SFATAL ;MOVE TO MAILBOX # ***** 230 *****
2177 011170 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
2178 011172 000000 HALT ;INTERRUPT DID NOT OCCUR FIRST,OR WRONG $TESTN
2179 ; TO SCOPE REPLACE HALT W/ 240
2180 ; AND REPLACE NEXT INST W/ 720
2181 011174 005067 166636 TR2: CLR 36

```



# E05

MAIN. MACY11 27(1006) 17-FEB-77 15:39 PAGE 56  
 DVKADB.P11 17-FEB-77 15:34 T63

TEST THAT A PENDING INTERRUPT OCCURS BEFORE TRAP

SEQ 0058

```

2182
2183
2184
2185
2186 011200 005237 000404
2187 011204 022737 000064 000404
2188 011212 001042
2189 011214 032767 000001 167176
2190 011222 001403
2191 011224 005767 167156
2192 011230 001055
2193 011232
2194 011232 042767 000100 166324
2195 011240 012706 000500
2196 011244 012767 000340 001644
2197 011252 106467 001640
2198 011256 012767 000100 166300
2199 011264 012767 011316 166542
2200 011272 012767 011332 166564
2201 011300 012767 011320 166512
2202 011306 012767 000340 166506
2203 011314 104400
2204 011316 000004
2205 011320
2206 011320 012737 000231 000402
2207 011326 005212
2208 011330 000000
2209
2210
2211 011332 005067 166464
2212 011336 005067 166524
2213 011342 012767 000066 166514
2214 011350 012767 000036 166456
2215 011356 012767 000022 166434
2216

:*****
:TEST 64 TEST THAT A PENDING INTERRUPT; INTERRUPTS BETWEEN TRAPS
:*****
↑ST64: INC @#STESTN ;UPDATE TEST NUMBER
      CMP #64,@#STESTN ;SEQUENCE ERROR?
      BNE TR5 ;BR TO ERROR HALT ON SEQ ERROR
      BIT #1,$ENV ;CHECK IF ON APT
      BEQ NOAPT1 ; IF NOT
      TST $PASS ; CHECK IF ON FIRST PASS
      BNE TST65 ; IF NOT

NOAPT1: BIC #100,TTCSR
        MOV #BUFF,%6
        MOV #340,$STATUS
        MTPS STATUS
        MOV #100,TTCSR
        MOV #TR3,34 ;TRAP
        MOV #TR4,64 ;TTY OUTPUT
        MOV #TR5,20 ;IOT
        MOV #340,22 ;IOT PRIORITY
        TRAP ;THE ACT OF TRAPPING LOWER PRIORITY
        IOT ;INTERRUPT SHOULD OCCUR IN PLACE OF IOT TRAP

TR3:
TR5: MOV #231,@#$FATAL ;MOVE TO MAILBOX # ***** 231 *****
      INC (R2) ;SET MSGTYP TO FATAL ERROR
      HALT ;NO INTERRUPT BETWEEN TRAPS, OR WRONG $TESTN
          ; TO SCOPE REPLACE HALT W/ 240
          ; AND REPLACE NEXT INST W/ 730
          ;CLR IOT PRIORITY

TR4: CLR 22
      CLR 66
      MOV #66,64
      MOV #36,34
      MOV #22,20
  
```

# F05

MAIN MACY11 27(1006) 17-FEB-77 15:39 PAGE 57  
CVKADB.P11 17-FEB-77 15:34 T64

TEST THAT A PENDING INTERRUPT; INTERRUPTS BETWEEN TRAPS

SEG 0059

2217  
2218  
2219  
2220  
2221  
2222  
2223  
2224  
2225  
2226  
2227  
2228  
2229  
2230  
2231  
2232  
2233  
2234  
2235  
2236  
2237  
2238  
2239  
2240  
2241

011364 005237 000404  
011370 022737 000065 000404  
011376 001026  
011400 106427 000340  
011404 012767 000100 166152  
011412 012767 000100 166140  
011420 000005  
011422 032767 000100 166134  
011430 001405  
011432 012737 000232 000402  
011440 005212  
011442 000000  
  
011444 032767 000100 166106 1\$:  
011452 001405  
011454 012737 000233 000402  
011462 005212  
011464 000000

```
*****  
;TEST 65 TEST THAT "RESET" GOES TO OUTSIDE WORLD  
*****  
TST65: INC @#STESTN ;UPDATE TEST NUMBER  
CMP #65,@#STESTN ;SEQUENCE ERROR?  
BNE TST66-12 ;BR TO ERROR HALT ON SEQ ERROR  
MTPS #340  
MOV #100,TTCSR ;SET INTERRUPT ENABLE  
MOV #100,TRCSR ;SET INTERRUPT ENABLE  
RESET ;SHOULD CLEAR INTERRUPT ENABLE  
BIT #100,TTCSR ;TEST FOR CLEAR  
BEQ 1$  
MOV #232,@#SFATAL ;MOVE TO MAILBOX # ***** 232 *****  
INC (R2) ;SET MSGTYP TO FATAL ERROR  
HALT ;RESET FAILED TO CLEAR TTCSR  
 ; TO SCOPE REPLACE HALT W/ 240  
 ; AND REPLACE NEXT INST W/ 755  
 ;TEST FOR CLEAR  
  
BIT #100,TRCSR  
BEQ TST66  
MOV #233,@#SFATAL ;MOVE TO MAILBOX # ***** 233 *****  
INC (R2) ;SET MSGTYP TO FATAL ERROR  
HALT ;RESET FAILED TO CLEAR TRCSR,OR WRONG STESTN  
 ; TO SCOPE REPLACE HALT W/ 240  
 ; AND REPLACE NEXT INST W/ 744
```



# G05

.MAIN. MACY11 27(1006) 17-FEB-77 15:39 PAGE 58  
 DVKADB.P11 17-FEB-77 15:34 T65

TEST THAT "RESET" GOES TO OUTSIDE WORLD

SEQ 0060

```

2242
2243
2244
2245
2246 011466 005237 000404
2247 011472 022737 000066 000404
2248 011500 001014
2249 011502 012706 000500
2250 011506 012767 011544 166300
2251 011514 012746 000020
2252 011520 012746 011526
2253 011524 000006
2254 011526 000005
2255 011530 000005
2256 011532
2257 011532 012737 000234 000402
2258 011540 005212
2259 011542 000000
2260
2261
2262 011544 005067 001346
2263 011550 106467 001342
2264 011554 012767 000016 166232
2265 011562 005067 166230

:*****
:TEST 66 TEST THAT RESET HAS NO EFFECT ON THE TRACE TRAP
:*****
TST66: INC @#STESTN ;UPDATE TEST NUMBER
      CMP #66,@#STESTN ;SEQUENCE ERROR?
      BNE RSTP3 ;BR TO ERROR HALT ON SEQ ERROR
      MOV #BUFF,%6 ;SET STACK
      MOV #RESET2,14 ;SET UP TRACE VECTOR
      MOV #20,-(SP) ;PUSH T BIT
      MOV #.+6,-(SP) ;PUSH PC
      RTT ;SET T BIT
      RESET ;SHOULD HAVE NO EFFECT
      RESET ;NO EFFECT

RSTP3: MOV #234,@#$FATAL ;MOVE TO MAILBOX # ***** 234 *****
      INC (R2) ;SET MSGTYP TO FATAL ERROR
      HALT ;TRACE TRAP FAILED,OR WRONG $TESTN
      ; TO SCOPE REPLACE HALT W/ 240
      ; AND REPLACE NEXT INST W/ 756
      ;CLEAR TRACK

RESET2: CLR STATUS
      MTPS STATUS
      MOV #16,14
      CLR 16 ;TRACE STATUS
  
```

# H05

```

2266
2267
2268 :*****
2269 :TEST 67 TEST THAT WHEN TTY INTERRUPTS IT POPS NEW STATUS
2270 :*****
2271
2272
2273
2274
2275
2276
2277
2278
2279
2280
2281
2282
2283
2284
2285
2286
2287
2288
2289
2290
2291
2292
2293
2294
2295
2296
2297
2298
2299
2300
2301
2302
2303
2304
2305
2306
2307
2308
2309
2310
2311
2312
2313
2314
011566 005237 000404
011572 022737 000067 000404
011600 001070
011602 032767 000001 166610
011610 001403
011612 005767 166570
011616 001073
011620
011620 000005
011622 012706 000500
011626 012767 011670 166230
011634 106427 000000
011640 012767 000357 166220
011646 052767 000100 165710
011654 000240
011656 012737 000235 000402
011664 005212
011666 000000
011670 106767 001222
011674 022767 000357 001214
011702 001405
011704 012737 000236 000402
011712 005212
011714 000000
011716 000005
011720 012706 000500
011724 012767 011750 166132
011732 005067 166130
011736 106427 000000
011742 052767 000100 165614
011750 106767 001142
011754 005767 001136
011760 001405
011762
011762 012737 000237 000402
011770 005212
011772 000000
011774 005067 165564
012000 012767 000066 166056

```

```

†ST67: INC @#STESTN ;UPDATE TEST NUMBER
        CMP #67,@#STESTN ;SEQUENCE ERROR?
        BNE RSTP4 ;BR TO ERROR HALT ON SEQ ERROR
        BIT #1,$ENV ;CHECK IF ON APT
        BEQ NOAPT2 ;IF NOT ON APT
        TST $PASS ;CHECK IF FIRST PASS
        BNE TST70 ;IF NOT

NOAPT2: RESET
        MOV #BUFF,%6 ;SET UP STACK
        MOV #TTY3,64 ;INTERRUPT VECTOR
        MTPS #0
        MOV #357,66 ;HIGH PRIORITY ON INTERRUPT
        BIS #100,TTCSR ;SHOULD SET INTERRUPT ENABLE & INTERRUPT
        NOP
        MOV #235,@#$FATAL ;MOVE TO MAILBOX # ***** 235 *****
        INC (R2) ;SET MSGTYP TO FATAL ERROR
        HALT ;NO INTERRUPT
        ; TO SCOPE REPLACE HALT W/ 240
        ; AND REPLACE NEXT INST W/ 744

TTY3: MFPS STATUS
        CMP #357,STATUS
        BEQ 1$
        MOV #236,@#$FATAL ;MOVE TO MAILBOX # ***** 236 *****
        INC (R2) ;SET MSGTYP TO FATAL ERROR
        HALT ;INTERRUPT DID NOT POP CORRECT STATUS
        ; TO SCOPE REPLACE HALT W/ 240
        ; AND REPLACE NEXT INST W/ 731

1$: RESET
        MOV #BUFF,%6 ;STACK SET UP
        MOV #TTY4,64 ;INTERRUPT VECTOR
        CLR 66 ;CLR NEW STATUS
        MTPS #0
        BIS #100,TTCSR ;SET INTERRUPT ENABLE
        MFPS STATUS
        TST STATUS
        BEQ RSTP4

RSTP4: MOV #237,@#$FATAL ;MOVE TO MAILBOX # ***** 237 *****
        INC (R2) ;SET MSGTYP TO FATAL ERROR
        HALT ;INTERRUPT DID NOT POP CORRECT STATUS,OR WRONG $TESTN
        ; TO SCOPE REPLACE HALT W/ 240
        ; AND REPLACE NEXT INST W/ 702

RST4: CLR TTCSR
        MOV #66,64

```



```

2315
2316
2317 ;THIS ROUTINE TESTS THAT NO LEGAL ADDRESS TRAPS.
2318 ;AND THAT AN ILLEGAL ADDRESS TRAPS TO LOCATION 4
2319 ;*****
2320 ;TEST 70 TEST NON-EXISTENT ADDRESS TRAPS
2321 ;*****
2322 012006 005237 000404 000404 ST70: INC @#STESTN ;UPDATE TEST NUMBER
2323 012012 022737 000070 000404 CMP #70,@#STESTN ;SEQUENCE ERROR?
2324 012020 001066 BNE AUTO1 ;BR TO ERROR HALT ON SEQ ERROR
2325
2326 ;THIS ROUTINE TESTS MEMORY UNTIL IT DOES A NXM STOP
2327 012022 000402 BR ADALL
2328 012024 000000 TSL: D
2329 012026 000000 CORH: D
2330 012030 005000 ADALL: CLR %0
2331 012032 005067 165750 CLR 6
2332 012036 012767 012072 165740 MOV #ATRAP,4 ;SET UP ADDRESS TRAP ENTRANCE
2333 012044 012706 000500 NOR: MOV #BUFF,$P
2334 012050 105720 TSTB (0)+ ;IF OUTSIDE OF CORE, TRAP TO 4
2335 012052 020027 160000 CMP %0,#160000 ;IS POINTER IN SIDE CORE
2336 012056 101772 BLOS NOR ;TEST THE REST OF CORE
2337 012060
2338 012060 012737 000240 000402 AUTO: MOV #240,@#SFATAL ;MOVE TO MAILBOX # ***** 240 *****
2339 012066 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
2340 012070 000000 HALT ;SHOULD HAVE TRAPED
2341 ; TO SCOPE REPLACE HALT W/ 240
2342 ; AND REPLACE NEXT INST W/ 753
2343
2344 012072 005300 ;RETURN HERE ON AN ADDRESS TRAP
2345 012074 010067 177726 ATRAP: DEC RO
2346 ;THIS ROUTINE DOES NXM TRAPS UNTIL IT FINDS AN EXISTANT MEMORY LOCATION
2347 012100 012700 160001 MOV #160001,RO ;MOVE THE FIRST NXM LOCATION IN CORH
2348 012104 012767 012142 165672 CTRAP: MOV #BTRAP,4 ;SET UP THE HIGHEST MEM LOCATION
2349 012112 012706 000500 MOV #BUFF,$P ;SET UP THE VECTOR
2350 012116 105740 TSTB -(RO)
2351 012120 005200 DTRAP: INC RO ;DOES IT EXIST?
2352 012122 020067 177700 CMP RO,CORH ;IF YES INCREMENT IT
2353 012126 001430 BEQ TRAPB ;IS IT THE SAME LOCATION?
2354 012130 012737 000241 000402 MOV #241,@#SFATAL ;MOVE TO MAILBOX # ***** 241 *****
2355 012136 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
2356 012140 000000 HALT ;CONTENTS OF RO AND CORH SHOULD HAVE BEEN EQUAL
2357 ; TO SCOPE REPLACE HALT W/ 240
2358 ; AND REPLACE NEXT INST W/ 727
2359 ; IF THIS COMPARISON FAILS IT MEANS
2360 ; THAT SOME LEGAL ADDRESS TRAPPED OR
2361 ; THAT AN ILLEGAL ADDRESS DID NOT TRAP
2362 012142 106767 000750 BTRAP: MFPS STATUS
2363 012146 005767 000744 TST STATUS
2364 012152 001405 BEQ 1$
2365 012154 012737 000242 000402 MOV #242,@#SFATAL ;MOVE TO MAILBOX # ***** 242 *****
2366 012162 005212 INC (R2) ;SET MSGTYP TO FATAL ERROR
2367 012164 000000 HALT ;NEW PSW SHOULD HAVE BEEN ZERO
2368 ; TO SCOPE REPLACE HALT W/ 240
2369 ; AND REPLACE NEXT INST W/ 715
2370 012166 026727 166302 012120 1$: CMP BUFF-4,#DTRAP

```

# J05

MAIN, MACY11 27(1006), 17-FEB-77 15:39 PAGE 61  
DVKADB.P11 17-FEB-77 15:34 170 TEST NON-EXISTENT ADDRESS TRAPS

SEG 0063

2371	012174	001743				BEG	CTRAP	
2372	012176				AUTO1:			
2373	012176	012737	000243	000402		MOV	#243,0#SFATAL	: MOVE TO MAILBOX # ***** 243 *****
2374	012204	005212				INC	(R2)	: SET MSGTYP TO FATAL ERROR
2375	012206	000000				HALT		: OLD PC WAS NOT SAVED OR WRONG \$TESTN
2376								: TO SCOPE REPLACE HALT W/ 240
2377								: AND REPLACE NEXT INST W/ 704
2378	012210	012767	000006	165566	TRAPB:	MOV	#6,4	
2379	012216	005067	165564			CLR	6	



# K05

```

2380
2381
2382
2383
2384 012222 005237 000404
2385 012226 022737 000071 000404
2386 012234 001070
2387 012236 032767 000001 166154
2388 012244 001403
2389 012246 005767 166134
2390 012252 001066
2391 012254 042767 000100 165302 NOAPT3:
2392 012262 012706 000500
2393 012266 012767 012362 165570
2394 012274 005067 165566
2395 012300 105767 165260 WATE1:
2396 012304 100375
2397 012306 012767 000015 165252
2398 012314 105767 165244 WATE2:
2399 012320 100375
2400 012322 012767 000015 165236
2401 012330 052767 000100 165226
2402 012336 005067 000554
2403 012342 106467 000550
2404 012346 000001 WATE3:
2405 012350 012737 000244 000402
2406 012356 005212
2407 012360 000000
2408
2409
2410 012362 106767 000530 WATE:
2411 012366 005767 000524
2412 012372 001405
2413 012374 012737 000245 000402
2414 012402 005212
2415 012404 000000
2416
2417
2418 012406 026727 166062 012350 1$:
2419 012414 001405
2420 012416
2421 012416 012737 000246 000402 REES1:
2422 012424 005212
2423 012426 000000
2424
2425
2426 012430 042767 000100 165126 REES:
2427 012436 012767 000066 165420

```

```

;*****
;TEST 71 TEST THE 'WAIT' INSTRUCTION
;*****
†ST71: INC @#STESTN ;UPDATE TEST NUMBER
CMP #71,@#STESTN ;SEQUENCE ERROR?
BNE REES1 ;BR TO ERROR HALT ON SEQ ERROR
BIT #1,SENV ;CHECK IF ON APT
BEQ NOAPT3 ;BR, IF NOT ON APT
TST $PASS ;CHECK IF FIRST PASS
BNE REES ;BR, IF NOT
NOAPT3: BIC #100,TPS ;CLEAR INTERRUPT ENABLE
MOV #BUFF,SP ;SET UP THE STACK
MOV #WATE,64 ;SET UP THE INTERRUPT VECTOR
CLR 66
WATE1: TSTB TPS ;WAIT FOR READY
BPL WATE1 ;TO BE UP
MOV #15,TPB ;DO A CARRIAGE RETURN
WATE2: TSTB TPS ;WAIT FOR READY TO COME UP
BPL WATE2
MOV #15,TPB ;DO ANOTHER CARRIAGE RETURN
BIS #100,TPS ;SET THE INTERRUPT ENABLE
CLR STATUS ;CLEAR THE PSW
MTPS STATUS
WATE3: WAIT ;WAIT FOR THE INTERRUPT
MOV #244,@#$FATAL ;MOVE TO MAILBOX # ***** 244 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;WAIT INSTRUCTION DID NOT LOOP
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 725
WATE: MFPS STATUS
TST STATUS ;IS THE PSW CORRECT?
BEQ 1$
MOV #245,@#$FATAL ;MOVE TO MAILBOX # ***** 245 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;NEW PSW SHOULD HAVE BEEN ZERO
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 713
1$: CMP BUFF-4,#WATE3+2 ;IS THE OLD PC SAVED
BEQ REES
REES1: MOV #246,@#$FATAL ;MOVE TO MAILBOX # ***** 246 *****
INC (R2) ;SET MSGTYP TO FATAL ERROR
HALT ;OLD PC WAS NOT SAVED OR WRONG $TESTN
; TO SCOPE REPLACE HALT W/ 240
; AND REPLACE NEXT INST W/ 702
REES: BIC #100,TPS ;CLEAR THE INTERRUPT ENABLE
MOV #66,64

```

```

2428
2429
2430
2431
2432 012444 005237 000404
2433 012450 022737 000072 000404
2434 012456 001002
2435 012460 000167 000013
2436 012464
2437 012464 012737 000247 000402
2438 012472 005212
2439 012474 000000
2440
2441
2442 012476 005307

;*****
;TEST 72 TEST ,THAT ODD ADDRESSING WILL IGNORE BIT 0
;*****
TST72: INC @#STESTN ;UPDATE TEST NUMBER
        CMP #72,@#STESTN ;SEQUENCE ERROR?
        BNE RSTP5 ;BR TO ERROR HALT ON SEQ ERROR
        JMP ODD+1
RSTP5: MOV #247,@#SFATAL ;MOVE TO MAILBOX # ***** 247 *****
        INC (R2) ;SET MSGTYP TO FATAL ERROR
        HALT ;SHOULD HAVE JUMPED,OR WRONG $TESTN
        ; TO SCOPE REPLACE HALT W/ 240
        ; AND REPLACE NEXT INST W/ 770
ODD: DEC PC

```



# M05

.MAIN. MACY11 27(1006) 17-FEB-77 15:39 PAGE 64  
 DVKADB.P11 17-FEB-77 15:34 T72 TEST , THAT ODD ADDRESSING WILL IGNORE BIT 0

SEQ 0066

```

2443
2444
2445
2446
2447 012500 005237 000404
2448 012504 022737 000073 000404
2449 012512 001136
2450 012514 010267 000534
2451 012520 010700
2452 012522 010704
2453 012524 010705
2454 012526 012703 013042
2455 012532 012302
2456 012534 012301
2457 012536 020267 000310
2458 012542 001014
2459 012544 032767 000300 165654
2460 012552 001403
2461 012554 062703 000004
2462 012560 000764
2463 012562 032767 000004 165632 1$:
2464 012570 001401
2465 012572 000757
2466 012574 020267 000262 2$:
2467 012600 001007
2468 012602 032767 000020 165612
2469 012610 001403
2470 012612 062703 000010
2471 012616 000745
2472 012620 020267 000242 3$:
2473 012624 001005
2474 012626 032767 000004 165566
2475 012634 001401
2476 012636 000735
2477 012640 020267 000232 4$:
2478 012644 001005
2479 012646 032767 000010 165546
2480 012654 001401
2481 012656 000725
2482 012660 020267 000216 5$:
2483 012664 001002
2484 012666 000167 000244
2485 012672 010267 000206
2486 012676 005267 000202 6$:
2487 012702 012767 012730 165100 GIN2:
2488 012710 012706 000500
2489 012714 005067 000176
2490 012720 106467 000172
2491 012724 000167 000154
2492
2493
2494 012730 010267 000104
2495 012734 016702 000314
2496 012740 020627 000474
2497 012744 001405
2498 012746 012737 000250 000402

```

```

;*****
;TEST 73 TEST THAT ALL RESERVED INSTRUCTIONS TRAP
;*****
TST73: INC J#STESTN ;UPDATE TEST NUMBER
CMP #73,J#STESTN ;SEQUENCE ERROR?
BNE RET4 ;BR TO ERROR HALT ON SEQ ERROR
MOV R2,R2STOR ;SAVE REG 2
MOV PC,%0 ;SET THESE
MOV PC,%4 ;REGISTERS
MOV PC,%5 ;TO EXISTENT MEMORY LOCATIONS
MOV #TABLE,TAB ;TABLE POINTER
GIN1: MOV (TAB)+,FIRST ;FIRST OR CURRENT INSTRUCTION
MOV (TAB)+,LAST ;LAST INSTRUCTION OR GROUP
CMP FIRST,EISFIS ;IS IT THE 'EISFIS' GROUP?
BNE 2$ ;NO
BIT #300,$CPUOP ;DO WE HAVE EISFIS OPTION?
BEQ 1$ ;NO
ADD #4,TAB ;IF YES DO NO DO THE
BR GIN1 ;EIS FIS OP CODES
BIT #4,$SWREG ;DO WE HAVE DIS INSTRUCTION SET
BEQ 2$ ;NO
BR GIN1 ;IF YES, DO NOT DO EIS OP CODES - DO JUST FIS
CMP FIRST,STOP ;IS IT THE STOP GROUP
BNE 3$ ;NO
BIT #20,$SWREG ;DO WE WANT TO DO IT?
BEQ 3$ ;YES
ADD #10,TAB ;SKIP ENTIRE STOP GROUP
BR GIN1 ;NO
CMP FIRST,DIS ;IS THIS THE DIS GROUP?
BNE 4$ ;NO
BIT #4,$SWREG ;DO WE HAVE DIS OPTION?
BEQ 4$ ;NO
BR GIN1 ;IF YES, SKIP THE DIS GROUP
CMP FIRST,STOP1 ;IS IT THE STOP1 GROUP?
BNE 5$ ;NO
BIT #10,$SWREG ;DO WE WANT TO DO IT?
BEQ 5$ ;YES
BR GIN1 ;NO
CMP FIRST,FINISH ;TEST ALL
BNE 6$ ;NO, BR 4$
JMP GIN3 ;YES, GO TO END OF PASS ROUTINE
GIN2: MOV FIRST,INST ;SET UP INST
INC INST ;SET UP RETURN FROM TRAP
MOV #RET,IO ;SET UP STACK POINTER
MOV #BUFF,SP ;CLEAR PRIORITY
CLR STATUS ;CLEAR PRIORITY
MTPS STATUS ;EXECUTE RESERVED INSTRUCTION
JMP INST

;TRAPPING SHOULD SEND YOU HERE
RET: MOV R2,R2SAVE ;SAVE REG 2
MOV R2STOR,R2 ;RESTORE MAILBOX POINTER
CMP SP,#BUFF-4 ;TEST DECREMENT OF SP
BEQ RET1
MOV #250,J#SFATAL ;MOVE TO MAILBOX # ***** 250 *****

```

# N05

.MAIN. MACY11 27(1006) 17-FEB-77 15:39 PAGE 65  
 DVKADB.P11 17-FEB-77 15:34 T73 TEST

THAT ALL RESERVED INSTRUCTIONS TRAP

SEG 0067

2499	012754	005212				INC	(R2)		;SET MSGTYP TO FATAL ERROR
2500	012756	000000				HALT			;WRONG DECREMENT
2501									; TO SCOPE REPLACE HALT W/ 240
2502									; AND REPLACE NEXT INST W/ 655
2503	012760	026727	165510	013106	RET1:	CMP	BUFF-4, #INST+2		;LOC OF INST UNINCREMENTED
2504	012766	001405				BEQ	RET2		
2505	012770	012737	000251	000402		MOV	#251, @#SFATAL		; MOVE TO MAILBOX # ***** 251 *****
2506	012776	005212				INC	(R2)		;SET MSGTYP TO FATAL ERROR
2507	013000	000000				HALT			;INST INC ON TRAP
2508									; TO SCOPE REPLACE HALT W/ 240
2509									; AND REPLACE NEXT INST W/ 644
2510	013002	005767	165470		RET2:	TST	BUFF-2		
2511	013006	001405				BEQ	RET3		
2512	013010				RET4:				
2513	013010	012737	000252	000402		MOV	#252, @#SFATAL		; MOVE TO MAILBOX # ***** 252 *****
2514	013016	005212				INC	(R2)		;SET MSGTYP TO FATAL ERROR
2515	013020	000000				HALT			;CONDITION CODES SET ON TRAP, OR WRONG \$TESTN
2516									; TO SCOPE REPLACE HALT W/ 240
2517									; AND REPLACE NEXT INST W/ 634
2518	013022	016702	000012		RET3:	MOV	R2SAVE, R2		; RESTORE REG 2
2519	013026	026701	000052			CMP	INST, LAST		
2520	013032	001637				BEQ	GIN1		;SET UP NEW GROUP
2521	013034	000167	177636			JMP	GIN2		;FINISH OLD GROUP
2522	013040	000000			R2SAVE:	.WORD	0		
2523									;END OF INSTRUCTION GROUP
2524	013042	006777			TABLE:	6777			
2525	013044	007777				7777			
2526	013046	106777				106777			
2527	013050	107777				107777			
2528	013052	067777			EISFIS:	67777			; IF WE HAVE THE EIS FIS OPTION
2529	013054	073777				73777			; THEN THE EISFIS GROUP
2530	013056	074777			FIS:	74777			; WILL BE SKIPEO
2531	013060	075037				75037			
2532	013062	075377			STOP:	75377			
2533	013064	076026				76026			
2534	013066	076027			DIS:	76027			
2535	013070	076057				76057			
2536	013072	076057				76057			
2537	013074	076777				76777			
2538	013076	167777			STOP1:	167777			
2539	013100	177777				177777			
2540	013102	013102			FINISH:	.			;END FLAG
2541	013104	000000			INST:	HALT			;WILL CONTINUE RESERVED INST
2542	013106	000404				BR	TERR		
2543	013110	000403				BR	TERR		
2544	013112	000402				BR	TERR		
2545	013114	000401				BR	TERR		
2546	013116	000000			STATUS:	0			
2547	013120	016702	000130		TERR:	MOV	R2STOR, R2		; RESTORE R2
2548	013124	012737	000255	000402		MOV	#255, @#SFATAL		; INDICATE ERROR
2549	013132	005212				INC	(R2)		
2550	013134	000000				HALT			
2551									
2552									
2553	013136	005237	000406		GIN3:	INC	@#SPASS		
2554	013142	105267	000110			INCB	PASSPT		;SHOULD PRINT THIS PASS?



# B06

MAIN. MACY11 27(1006) 17-FEB-77 15:39 PAGE 66  
 DVKADB.P11 17-FEB-77 15:34 T73 TEST

THAT ALL RESERVED INSTRUCTIONS TRAP

SEG 0068

2555	013146	001023				BNE	ACT		;NO
2556	013150	132767	000040	165243		BITB	#40,SEVM		;WILL APT ALLOW PRINTING?
2557	013156	001017				BNE	ACT		;NO
2558	013160	012700	013263			MOV	#MSG,RO		;GET MSG ADDR.
2559	013164	105737	177564		WAIT:	TSTB	@TPS		;TTY READY
2560	013170	100375				BPL	WAIT		;NO WAIT
2561	013172	112037	177566			MOVB	(RO)+,@TPB		;PRINT CHARACTER
2562	013176	001372				BNE	WAIT		;NEXT IF NOT DONE.
2563	013200	105737	177564		WAIT1:	TSTB	@TPS		
2564	013204	100375				BPL	WAIT1		
2565	013206	000005				RESET			
2566	013210	012767	177761	000040		MOV	#177761,PASSPT		;DO IT 15 DECIMAL TIMES
2567	013216	013700	000042		ACT:	MOV	@42,RO		;CHECK ACT
2568	013222	001405				BEQ	GOAGIN		;KEEP GOING
2569	013224	000005				RESET			
2570	013226	004710			SENDAD:	JSR	PC,(RO)		;ACT HOOKS
2571	013230	000240				NOP			
2572	013232	000240				NOP			
2573	013234	000240				NOP			
2574	013236	012767	000012	164544	GOAGIN:	MOV	#12,10		
2575	013244	005067	164542			CLR	12		
2576	013250	000167	165324			JMP	RESTRT		;DO NEXT PASS
2577	013254	000000			R2STOR:	.WORD	0		
2578	013256	177777			PASSPT:	-1			
2579	013260	005015	047105	020104	MSG:	.ASCIZ	<15><12>.END OF PASS.		
2580	013266	043117	050040	051501					
2581	013274	000123							

```

2582
2583
2584 ;*****
2585 ;POWER FAIL ROUTINE
2586 ;*****
2587
2588 013276 012767 013306 164520 PWRDWN: MOV #PWRUP,24
2589 013304 000000 HALT
2590
2591 013306 012767 013276 164510 PWRUP: MOV #PWRDWN,24
2592 013314 012706 000500 MOV #BUFF,SP
2593 013320 132767 000040 165073 BITB #40,$ENVM ;WILL APT ALLOW PRINTING?
2594 013326 001013 BNE PFRES ;NO
2595 013330 012700 013362 MOV #MSGPWF,RO ;GET MSG ADDR.
2596 013334 105737 177564 PWAIT: TSTB @#TPS ;TTY READY
2597 013340 100375 BPL PWAIT ;NO WAIT
2598 013342 112037 177566 MOVB (RO)+,@#TPB ;PRINT CHARACTER
2599 013346 001372 BNE PWAIT ;NEXT IF NOT DONE.
2600 013350 105737 177564 PWAIT1: TSTB @#TPS
2601 013354 100375 BPL PWAIT1
2602 013356 000167 165120 PFRES: JMP START
2603 013362 005015 047520 042527 MSGPWF: .ASCIZ <15><12>.POWER FAILED!.
2604 013370 020122 040506 046111
2605 013376 042105 000041
2606 000001 .END
    
```



ABASE =	000000	260		
ACDW1 =	000000	260		
ACDW2 =	000000	260		
ACPUOP =	000000	260	275	
ACT	013216	2555	2557	2567#
ADALL	012030	2327	2330#	
ADDW0 =	000000	260		
ADDW1 =	000000	260		
ADDW10 =	000000	260		
ADDW11 =	000000	260		
ADDW12 =	000000	260		
ADDW13 =	000000	260		
ADDW14 =	000000	260		
ADDW15 =	000000	260		
ADDW2 =	000000	260		
ADDW3 =	000000	260		
ADDW4 =	000000	260		
ADDW5 =	000000	260		
ADDW6 =	000000	260		
ADDW7 =	000000	260		
ADDW8 =	000000	260		
ADDW9 =	000000	260		
ADEVCT =	000000	260	266	
ADEVM =	000000	260		
AENV =	000000	260	271	
AENVN =	000000	260	272	
AFATAL =	000000	260	263	
AMADR1 =	000000	260	288	
AMADR2 =	000000	260	292	
AMADR3 =	000000	260	295	
AMADR4 =	000000	260	298	
AMAMS1 =	000000	260	282	
AMAMS2 =	000000	260	230	
AMAMS3 =	000000	260	293	
AMAMS4 =	000000	260	296	
AMSGAD =	000000	260	268	
AMSGLG =	000000	260	269	
AMSGTY =	000000	260	262	
AMTYP1 =	000000	260	283	
AMTYP2 =	000000	260	291	
AMTYP3 =	000000	260	294	
AMTYP4 =	000000	260	297	
APASS =	000000	260	265	
APRIOR =	000000	260		
ASWREG =	000000	260	273	
ATESTN =	000000	260	264	
ATRAP	012072	2332	2344#	
AUNIT =	000000	260	267	
AUSWR =	000000	260	274	
AUTO	012060	2337#		
AUTO1	012176	2324	2372#	
AVECT1 =	000000	260		
AVECT2 =	000000	260		
BEGIN	000572	335	344	349#
BELL =	000240	235#		
BTRAP	012142	2348	2362#	





RA	005436	1381	1390*		
RA1	003662	1017	1026*		
RB	005422	1380*	1383*	1390*	1391
RBBB	005424	1379	1384*		
RB1	003646	1016*	1019*	1026*	1027
RB1AA	003650	1015	1020*		
RC	005416	1382*	1392		
RC1	003642	1018*	1028		
REES	012430	2390	2419	2426*	
REES1	012416	2386	2420*		
RESET2	011544	2250	2262*		
RESTRT	000600	350*	2576		
RET	012730	2487	2494*		
RETA	002200	675	682*		
RETAT	010040	1925	1935*		
RETA1	003034	848	855*		
RETA2	003752	1038	1045*		
RETA3	004606	1211	1218*		
RETA4	005526	1402	1409*		
RETA5	006362	1583	1590*		
RETB	002230	690	692*		
RETB1	010114	1943	1953*		
RETB2	003064	863	865*		
RETB3	004002	1053	1055*		
RETB4	004636	1226	1228*		
RETB5	005556	1418	1420*		
RETB6	006412	1598	1600*		
RETC	002300	707	709*		
RETC1	010174	1968	1973*		
RETC2	003134	879	881*		
RETC3	004052	1070	1072*		
RETC4	004706	1242	1244*		
RETC5	005626	1434	1436*		
RETC6	006462	1615	1617*		
RETD	002364	723	728*		
RETD1	003220	896	901*		
RETD2	004136	1086	1091*		
RETD3	004772	1259	1264*		
RETD4	005712	1451	1456*		
RETD5	006546	1631	1636*		
RETE	002436	736	741*		
RETE1	003270	909	913*		
RETE2	004210	1099	1104*		
RETE3	005044	1272	1277*		
RETE4	005764	1464	1469*		
RETE5	006620	1644	1649*		
RETF	002514	756	759*		
RETF1	003346	928	931*		
RETF2	004266	1119	1122*		
RETF3	005122	1292	1295*		
RETF4	006042	1484	1487*		
RETF5	006676	1664	1667*		
RETG	002644	796	799*		
RETG1	003476	968	971*		
RETG2	004416	1159	1162*		
RETG3	005252	1332	1335*		











# JOB

MAIN MACY11 27(1006) 17-FEB-77 15:39 PAGE 75  
 DVKADB.P11 17-FEB-77 15:34

## CROSS REFERENCE TABLE -- USER SYMBOLS

SEQ 0076

	1710#	1716	1717#	1723	1724#	1730	1731#	1739	1740#	1754	1755#	1771	1772#	
	1788	1789#	1808	1809#	1821	1822#	1839	1840#	1846	1847#	1853	1854#	1860	
	1861#	1868	1869#	1879	1880#	1886	1887#	1893	1894#	1900	1901#	1910	1911#	
	1930	1931#	1948	1949#	1955	1956#	1975	1976#	1997	1998#	2021	2022#	2030	
	2031#	2050	2051#	2058	2059#	2082	2083#	2090	2091#	2111	2112#	2118	2119#	
	2136	2137#	2170	2171#	2176	2177#	2206	2207#	2230	2231#	2237	2238#	2257	
	2258#	2285	2286#	2293	2294#	2308	2309#	2338	2339#	2354	2355#	2365	2366#	
	2373	2374#	2405	2406#	2413	2414#	2421	2422#	2437	2438#	2498	2499#	2505	
	2506#	2513	2514#											
ERROR=	000402	242#	353#											
SETABL	000420	270#												
SETEND	000450	299#	322											
SFATAL	000402	242	263#	377*	387*	397*	408*	419*	430*	441*	451*	470*	483*	496*
		509#	522*	536*	544*	553*	561*	568*	576*	584*	592*	608*	615*	622*
		629#	641*	648*	655*	662*	677*	694*	711*	730*	743*	761*	768*	775*
		782#	790*	801*	808*	815*	822*	833*	850*	867*	883*	903*	915*	933*
		940#	947*	954*	962*	973*	980*	987*	994*	1004*	1021*	1040*	1057*	1074*
		1093#	1106*	1124*	1131*	1138*	1145*	1153*	1164*	1171*	1178*	1185*	1196*	1213*
		1230#	1246*	1266*	1279*	1297*	1304*	1311*	1318*	1326*	1337*	1344*	1351*	1358*
		1368#	1385*	1404*	1422*	1438*	1458*	1471*	1489*	1496*	1503*	1510*	1518*	1529*
		1536#	1543*	1550*	1561*	1585*	1602*	1619*	1638*	1651*	1669*	1676*	1683*	1690*
		1698#	1709*	1716*	1723*	1730*	1739*	1754*	1771*	1788*	1808*	1821*	1839*	1846*
		1853#	1860*	1868*	1879*	1886*	1893*	1900*	1910*	1930*	1948*	1955*	1975*	1997*
		2021#	2030*	2050*	2058*	2082*	2090*	2111*	2118*	2136*	2170*	2176*	2206*	2230*
		2237#	2257*	2285*	2293*	2308*	2338*	2354*	2365*	2373*	2405*	2413*	2421*	2437*
		2498#	2505*	2513*	2548*									
		317#												
SHIBTS	000450	288#												
SMADR1	000432	292#												
SMADR2	000436	295#												
SMADR3	000442	298#												
SMADR4	000446	261#	318	322										
SMAIL	000400	282#												
SMAMS1	000430	290#												
SMAMS2	000434	293#												
SMAMS3	000440	296#												
SMAMS4	000444	318#												
SMBADR	000452	268#												
SMSGAD	000414	269#												
SMSGLG	000416	262#	350	351*										
SMSGTY	000400	283#												
SMTYP1	000431	291#												
SMTYP2	000435	294#												
SMTYP3	000441	297#												
SMTYP4	000445	265#	328*	2153	2191	2275	2389	2553*						
SPASS	000406	320#												
SPASTM	000456	251#	256											
SSVPC =	000400	208#												
SSWR =	000000	273#	338	342	2463	2468	2474	2479						
SSWREG	000422	241	264#	370*	371	460*	461	531*	532	601*	602	671*	672	686*
STESTN	000404	687	703#	704	719*	720	752*	753	844*	845	859*	860	875*	876
		892#	893	924*	925	1013*	1014	1034*	1035	1049*	1050	1066*	1067	1082*
		1083	1115*	1116	1207*	1208	1222*	1223	1238*	1239	1255*	1256	1288*	1289
		1377#	1378	1398*	1399	1414*	1415	1430*	1431	1447*	1448	1480*	1481	1579*
		1580	1594*	1595	1611*	1612	1627*	1628	1660*	1661	1748*	1749	1763*	1764
		1780#	1781	1797*	1798	1830*	1831	1921*	1922	1939*	1940	1964*	1965	1985*

# K06

.MAIN. MACY11 27(1006) 17-FEB-77 15:39 PAGE 76  
 DVKADB.P11 17-FEB-77 15:34

## CROSS REFERENCE TABLE -- USER SYMBOLS

SEG 0077

	1986	2008*	2009	2040*	2041	2067*	2068	2101*	2102	2126*	2127	2148*	2149
	2186*	2187	2221*	2222	2246*	2247	2270*	2271	2322*	2323	2384*	2385	2432*
\$TN = 000074	2433	2447*	2448										
	208#	367	373#	450	457	463#	521	528	534#	552	591	598	604#
	661	668	674#	683	689#	693	700	706#	710	716	722#	742	749
	755#	841	847*	856	862#	866	872	878#	882	889	895#	914	921
	927#	1003	1010	1016#	1031	1037#	1046	1052#	1056	1063	1069#	1073	1079
	1085#	1105	1112	1118#	1204	1210#	1219	1225#	1229	1235	1241#	1245	1252
	1258#	1278	1285	1291#	1367	1374	1380#	1395	1401#	1411	1417#	1421	1427
	1433#	1437	1444	1450#	1470	1477	1483#	1576	1582#	1591	1597#	1601	1608
	1614#	1618	1624	1630#	1650	1657	1663#	1738	1745	1751#	1760	1766#	1770
	1777	1783#	1787	1794	1800#	1820	1827	1833#	1918	1924#	1936	1942#	1954
	1961	1967#	1974	1982	1988#	1996	2005	2011#	2037	2043#	2057	2064	2070#
	2098	2104#	2117	2123	2129#	2145	2151#	2183	2189#	2218	2224#	2236	2243
	2249#	2267	2273#	2319	2325#	2381	2387#	2429	2435#	2444	2450#		
\$TSTM 000454	319#												
\$TSTNM= 000404	241#	352*											
\$UNIT 000412	267#												
\$UNITM 000460	321#												
\$USWR 000424	274#												
\$X = 012514	373#												
	512	380	390	400	411	422	433	444	454	463#	473	486	499
	618	525	534#	539	547	556	564	571	579	587	595	604#	611
	722#	625	632	644	651	658	665	674#	680	689#	697	706#	714
	836	733	746	755#	764	771	778	785	793	804	811	818	825
	950	847#	853	862#	870	878#	886	895#	906	918	927#	936	943
	1060	957	965	976	983	990	997	1007	1016#	1024	1037#	1043	1052#
	1174	1069#	1077	1085#	1096	1109	1118#	1127	1134	1141	1148	1156	1167
	1291#	1181	1188	1199	1210#	1216	1225#	1233	1241#	1249	1258#	1269	1282
	1401#	1300	1307	1314	1321	1329	1340	1347	1354	1361	1371	1380#	1388
	1513	1407	1417#	1425	1433#	1441	1450#	1461	1474	1483#	1492	1499	1506
	1630#	1521	1532	1539	1546	1553	1564	1582#	1588	1597#	1605	1614#	1622
	1742	1641	1654	1663#	1672	1679	1686	1693	1701	1712	1719	1726	1733
	1856	1751#	1757	1766#	1774	1783#	1791	1800#	1811	1824	1833#	1842	1849
	1967#	1863	1871	1882	1889	1896	1903	1913	1924#	1933	1942#	1951	1958
	2104#	1978	1988#	2000	2011#	2024	2033	2043#	2053	2061	2070#	2085	2093
	2249#	2114	2121	2129#	2139	2151#	2173	2179	2189#	2209	2224#	2233	2240
	2416	2260	2273#	2288	2296	2311	2325#	2341	2357	2368	2376	2387#	2408
\$XX = 177635	380#	390#	400#	411#	422#	433#	444#	454#	473#	486#	499#	512#	525#
	539#	547#	556#	564#	571#	579#	587#	595#	611#	618#	625#	632#	644#
	651#	658#	665#	680#	697#	714#	733#	746#	764#	771#	778#	785#	793#
	804#	811#	818#	825#	836#	853#	870#	886#	906#	918#	936#	943#	950#
	957#	965#	976#	983#	990#	997#	1007#	1024#	1043#	1060#	1077#	1096#	1109#
	1127#	1134#	1141#	1148#	1156#	1167#	1174#	1181#	1188#	1199#	1216#	1233#	1249#
	1269#	1282#	1300#	1307#	1314#	1321#	1329#	1340#	1347#	1354#	1361#	1371#	1388#
	1407#	1425#	1441#	1461#	1474#	1492#	1499#	1506#	1513#	1521#	1532#	1539#	1546#
	1553#	1564#	1588#	1605#	1622#	1641#	1654#	1672#	1679#	1686#	1693#	1701#	1712#
	1719#	1726#	1733#	1742#	1757#	1774#	1791#	1811#	1824#	1842#	1849#	1856#	1863#
	1871#	1882#	1889#	1896#	1903#	1913#	1933#	1951#	1958#	1978#	2000#	2024#	2033#
	2053#	2061#	2085#	2093#	2114#	2121#	2139#	2173#	2179#	2209#	2233#	2240#	2260#
	2288#	2296#	2311#	2341#	2357#	2368#	2376#	2408#	2416#	2424#	2440#	2501#	2508#
\$XXX = 000634	2516#												
	380#	390#	400#	411#	422#	433#	444#	454#	473#	486#	499#	512#	525#
	539#	547#	556#	564#	571#	579#	587#	595#	611#	618#	625#	632#	644#
	651#	658#	665#	680#	697#	714#	733#	746#	764#	771#	778#	785#	793#
	804#	811#	818#	825#	836#	853#	870#	886#	906#	918#	936#	943#	950#



CROSS REFERENCE TABLE -- USER SYMBOLS

957#	965#	976#	983#	990#	997#	1007#	1024#	1043#	1060#	1077#	1096#	1109#
1127#	1134#	1141#	1148#	1156#	1167#	1174#	1181#	1188#	1199#	1216#	1233#	1249#
1269#	1282#	1300#	1307#	1314#	1321#	1329#	1340#	1347#	1354#	1361#	1371#	1388#
1407#	1425#	1441#	1461#	1474#	1492#	1499#	1506#	1513#	1521#	1532#	1539#	1546#
1553#	1564#	1588#	1605#	1622#	1641#	1654#	1672#	1679#	1686#	1693#	1701#	1712#
1719#	1726#	1733#	1742#	1757#	1774#	1791#	1811#	1824#	1842#	1849#	1856#	1863#
1871#	1882#	1889#	1896#	1903#	1913#	1933#	1951#	1958#	1978#	2000#	2024#	2033#
2053#	2061#	2085#	2093#	2114#	2121#	2139#	2173#	2179#	2209#	2233#	2240#	2260#
2288#	2296#	2311#	2341#	2357#	2368#	2376#	2408#	2416#	2424#	2440#	2501#	2508#
2516#												
244#	246#	251	252#	254#	256#	306	307#	309#	311#	325#	327#	330#
373	380	390	400	411	422	433	444	454	463	473	486	499
512	525	534	539	547	556	564	571	579	587	595	604	611
618	625	632	644	651	658	665	674	680	689	697	706	709
714	722	733	746	755	764	771	778	785	793	804	811	818
825	836	847	853	862	870	878	881	886	895	906	918	927
936	943	950	957	965	976	983	990	997	1007	1016	1024	1037
1043	1052	1060	1069	1072	1077	1085	1096	1109	1118	1127	1134	1141
1148	1156	1167	1174	1181	1188	1199	1210	1216	1225	1233	1241	1244
1249	1258	1269	1282	1291	1300	1307	1314	1321	1329	1340	1347	1354
1361	1371	1380	1388	1401	1407	1417	1425	1433	1436	1441	1450	1461
1474	1483	1492	1499	1506	1513	1521	1532	1539	1546	1553	1564	1582
1588	1597	1605	1614	1617	1622	1630	1641	1654	1663	1672	1679	1686
1693	1701	1712	1719	1726	1733	1742	1751	1757	1766	1774	1783	1791
1800	1811	1824	1833	1842	1849	1856	1863	1871	1882	1889	1896	1903
1913	1924	1927	1933	1942	1945	1951	1958	1967	1970	1973	1978	1988
2000	2011	2024	2033	2043	2053	2061	2070	2079	2085	2093	2104	2108
2114	2121	2129	2139	2151	2157	2173	2179	2189	2209	2224	2233	2240
2249	2252	2260	2273	2288	2296	2311	2325	2341	2357	2368	2376	2387
2408	2416	2424	2435	2440	2450	2501	2508	2516	2540			
306#	311											

= 013402

.\$X = 000450

ERROR	208#	376	386	396	407	418	429	440	450	469	482	495	508	521	535
	543	552	560	567	575	583	591	607	613	620	627	640	646	653	660
	677	693	710	729	742	760	766	773	780	789	800	806	813	820	831
	850	866	882	902	914	932	938	945	952	961	972	978	985	992	1003
	1020	1040	1056	1073	1092	1105	1123	1129	1136	1143	1152	1163	1169	1176	1183
	1194	1213	1229	1245	1265	1278	1296	1302	1309	1316	1325	1336	1342	1349	1356
	1367	1384	1404	1421	1437	1457	1470	1488	1494	1501	1508	1517	1528	1534	1541
	1548	1559	1585	1601	1618	1637	1650	1668	1674	1681	1688	1697	1708	1714	1721
	1728	1738	1754	1770	1787	1807	1820	1838	1844	1851	1858	1867	1878	1884	1891
	1898	1908	1930	1948	1954	1974	1996	2021	2029	2050	2057	2082	2088	2111	2117
	2136	2169	2175	2205	2229	2236	2256	2285	2292	2306	2337	2353	2364	2371	2405
	2412	2419	2436	2497	2504	2511									
LOOP	208#	380	390	400	411	422	433	444	454	473	486	499	512	525	539
	547	556	564	571	579	587	595	611	618	625	632	644	651	658	665
	680	697	714	733	746	764	771	778	785	793	804	811	818	825	836
	853	870	886	906	918	936	943	950	957	965	976	983	990	997	1007
	1024	1043	1060	1077	1096	1109	1127	1134	1141	1148	1156	1167	1174	1181	1188
	1199	1216	1233	1249	1269	1282	1300	1307	1314	1321	1329	1340	1347	1354	1361
	1371	1388	1407	1425	1441	1461	1474	1492	1499	1506	1513	1521	1532	1539	1546
	1553	1564	1588	1605	1622	1641	1654	1672	1679	1686	1693	1701	1712	1719	1726
	1733	1742	1757	1774	1791	1811	1824	1842	1849	1856	1863	1871	1882	1889	1896
	1903	1913	1933	1951	1958	1978	2000	2024	2033	2053	2061	2085	2093	2114	2121
	2139	2173	2179	2209	2233	2240	2260	2288	2296	2311	2341	2357	2368	2376	2408
	2416	2424	2440	2501	2508	2516									
NEWTST	208#	367	457	528	598	668	683	700	716	749	841	856	872	889	921
	1010	1031	1046	1063	1079	1112	1204	1219	1235	1252	1285	1374	1395	1411	1427
	1444	1477	1576	1591	1608	1624	1657	1745	1760	1777	1794	1827	1918	1936	1961
	1982	2005	2037	2064	2098	2123	2145	2183	2218	2243	2267	2319	2381	2429	2444
STARS	208#	249	259	303	305	312	367	369	457	459	528	530	598	600	668
	670	683	685	700	702	716	718	749	751	841	843	856	858	872	874
	889	891	921	923	1010	1012	1031	1033	1046	1048	1063	1065	1079	1081	1112
	1114	1204	1206	1219	1221	1235	1237	1252	1254	1285	1287	1374	1376	1395	1397
	1411	1413	1427	1429	1444	1446	1477	1479	1576	1578	1591	1593	1608	1610	1624
	1626	1657	1659	1745	1747	1760	1762	1777	1779	1794	1796	1827	1829	1918	1920
	1936	1938	1961	1963	1982	1984	2005	2007	2037	2039	2064	2066	2098	2100	2123
	2125	2145	2147	2183	2185	2218	2220	2243	2245	2267	2269	2319	2321	2381	2383
	2429	2431	2444	2446											
\$\$ERCD	208#	377	387	397	408	419	430	441	451	470	483	496	509	522	536
	544	553	561	568	576	584	592	608	615	622	629	641	648	655	662
	677	694	711	730	743	761	768	775	782	790	801	808	815	822	833
	850	867	883	903	915	933	940	947	954	962	973	980	987	994	1004
	1021	1040	1057	1074	1093	1106	1124	1131	1138	1145	1153	1164	1171	1178	1185
	1196	1213	1230	1246	1266	1279	1297	1304	1311	1318	1326	1337	1344	1351	1358
	1368	1385	1404	1422	1438	1458	1471	1489	1496	1503	1510	1518	1529	1536	1543
	1550	1561	1585	1602	1619	1638	1651	1669	1676	1683	1690	1698	1709	1716	1723
	1730	1739	1754	1771	1788	1808	1821	1839	1846	1853	1860	1868	1879	1886	1893
	1900	1910	1930	1948	1955	1975	1997	2021	2030	2050	2058	2082	2090	2111	2118
	2136	2170	2176	2206	2230	2237	2257	2285	2293	2308	2338	2354	2365	2373	2405
	2413	2421	2437	2498	2505	2513									
\$\$ERNU	208#	377	387	397	408	419	430	441	451	470	483	496	509	522	536
	544	553	561	568	576	584	592	608	615	622	629	641	648	655	662
	677	694	711	730	743	761	768	775	782	790	801	808	815	822	833
	850	867	883	903	915	933	940	947	954	962	973	980	987	994	1004
	1021	1040	1057	1074	1093	1106	1124	1131	1138	1145	1153	1164	1171	1178	1185
	1196	1213	1230	1246	1266	1279	1297	1304	1311	1318	1326	1337	1344	1351	1358
	1368	1385	1404	1422	1438	1458	1471	1489	1496	1503	1510	1518	1529	1536	1543



CROSS REFERENCE TABLE -- MACRO NAMES

SEQ 0080

	1550	1561	1585	1602	1619	1638	1651	1669	1676	1683	1690	1698	1709	1716	1723
	1730	1739	1754	1771	1788	1808	1821	1839	1846	1853	1860	1868	1879	1886	1893
	1900	1910	1930	1948	1955	1975	1997	2021	2030	2050	2058	2082	2090	2111	2118
	2136	2170	2176	2206	2230	2237	2257	2285	2293	2308	2338	2354	2365	2373	2405
SSERRO	2413	2421	2437	2498	2505	2513									
	208#	450	521	552	591	661	693	710	742	866	882	914	1003	1056	1073
	1105	1229	1245	1278	1367	1421	1437	1470	1501	1618	1650	1738	1770	1787	1820
SSLOOP	1954	1974	1996	2057	2117	2236									
	208#	380	390	400	411	422	433	444	454	473	486	499	512	525	539
	547	556	564	571	579	587	595	611	618	625	632	644	651	658	665
	680	697	714	733	746	764	771	778	785	793	804	811	818	825	836
	853	870	886	906	918	936	943	950	957	965	976	983	990	997	1007
	1024	1043	1060	1077	1096	1109	1127	1134	1141	1148	1156	1167	1174	1181	1188
	1199	1216	1233	1249	1269	1282	1300	1307	1314	1321	1329	1340	1347	1354	1361
	1371	1388	1407	1425	1441	1461	1474	1492	1499	1506	1513	1521	1532	1539	1546
	1553	1564	1588	1605	1622	1641	1654	1672	1679	1686	1693	1701	1712	1719	1726
	1733	1742	1757	1774	1791	1811	1824	1842	1849	1856	1863	1871	1882	1889	1896
	1903	1913	1933	1951	1958	1978	2000	2024	2033	2053	2061	2085	2093	2114	2121
	2139	2173	2179	2209	2233	2240	2260	2288	2296	2311	2341	2357	2368	2376	2408
SSNEWT	2416	2424	2440	2501	2508	2516									
	208#	367	457	528	598	668	683	700	716	749	841	856	872	889	921
	1010	1031	1046	1063	1079	1112	1204	1219	1235	1252	1285	1374	1395	1411	1427
	1444	1477	1576	1591	1608	1624	1657	1745	1760	1777	1794	1827	1918	1936	1961
	1982	2005	2037	2064	2098	2123	2145	2183	2218	2243	2267	2319	2381	2429	2444
.SACT1	244#	247													
.SAPT8	244#	257													
.SAPTH	244#	301													

. ABS. 013402 000

ERRORS DETECTED: 0  
 % DEFAULT GLOBALS GENERATED: 1

DVKADB, DVKADB/SOL/CRF/DS:ERFLZ=DVKADB.P11  
 RUN-TIME: 15 10 1 SECONDS  
 RUN-TIME RATIO: 266/27=9.6  
 CORE USED: 9K (18 PAGES)

B07



